



# ITT

Interconnect Solutions  
Cannon, VEAM, BIW


Providing **100% reliable**  
electrical connections for over **65 years**  
on commercial and **military aircrafts**  
and over a **150 billion** miles flown



*Engineered for life*

**DPXA - Single Shell DPX**

DPXA connectors are one-piece shell miniature rack/panel connectors. The construction offers high strength and maximum utilization of insert area for contact arrangements accommodating up to 106 contacts. Shells are keystone-shaped for polarization. Operating temperature for the DPXA is -54.2°C to +125°C (-67°F to +257°F).



DPXA-34



DPXB-33

**DPXB - Polarized ARINC Shell**

DPXB connectors are DPXA connectors with an ARINC B shelf. Additional polarization is provided by three hexagonal polarizing posts.

**DPX2 - Two Gang DPX Series**

DPX2 connectors are the original two-gang versions of the DPX, and are made of the same materials and accommodate the same contact arrangements. Keystone shaped shells accommodate two DPX inserts with up to 212 contacts. The DPX2 has three polarizing posts with 99 polarizing positions.



DPX2-34B



DPX2-33B

**DPX2 - A - ARINC A Shell**

DPX2-A connectors are DPX2 connectors with an ARINC A shell. This shell type has the receptacle flange placed .344 (8.74) from the front of the engaging portion of the shell, and short aluminum alloy polarizing posts permit polarization before contacts engage.

**DPX2-B - ARINC B Shell**

DPX2-B connectors supersede the DPX2-A and have an ARINC B Shell. This Shell type has the


receptacle flange placed .060 (1.52) from the front of the engaging portion of the shell, and polarizing posts permit polarization before the shells engage.

**DPX3 - Three Gang DPX Series**

DPX3 connectors are three-gang versions of the DPX, made of the same materials, and accommodate the same contact arrangements. The three-gang version can therefore accommodate up to a total of 318 in the keystone shaped shells, with three polarizing posts that are capable of providing up to 99 polarizing positions.



DPX3-34



DPX4-33

**DPX4 - Four Gang DPX Series**

DPX4 connectors are four gang versions of the DPX, made of the same materials, and can accommodate four separate arrangements that can total up to 424 contacts. The DPX4 has three polarizing posts with 99 polarizing positions.

**DPX\*MA - LITTLE CAESAR® Contact Assembly**

DPX\*MA connectors are DPX connectors with the LITTLE CAESAR contact assembly for rear insertion, release, and extraction of crimp type contacts. Insertion requires no tool; extraction requires an expendable plastic tool. A hard dielectric, closed-entry socket insert has lead-in chamfers for positive mating of contacts. Contacts are crimpable with the M22501 tool.

**DPX\*ME - Environmental with LITTLE CAESAR® Contact Assembly**

DPX\*ME connectors are DPXMA connectors with environmental interfacial and grommet seals, and olive drab shell finish.

**Performance and Material Specifications (DPXA/DPXB/DPX\*MA/DPX\*ME)**

|                      |             | DPXA/DPXB/DPX2                     | DPX*MA/DPX2*MA/ME                                            | Specifications |
|----------------------|-------------|------------------------------------|--------------------------------------------------------------|----------------|
| Shell                | Material    | Aluminum alloy                     | Aluminum alloy                                               | QQ- A-591/A380 |
|                      | Finish      | Cadmium plate with yellow chromate | Cadmium plate with yellow chromate for MA; olive drab for ME | QQ-P-416       |
| Insulator            | Material    | Melamine or Phenolic               | Diallyl phthalate or epoxy                                   | MIL-M-14       |
|                      | Material    | Copper alloy                       | Copper alloy                                                 | QQ-C-533       |
| Contacts             | Finish      | Gold                               | Gold                                                         | MIL-G-45204    |
|                      | Termination | Solder Pot                         | Crimp                                                        | N/A            |
| Polarizing Posts     | Material    | Die Cast                           | Die cast                                                     |                |
|                      | Finish      | Cadmium                            | Cadmium                                                      | QQ-P-416       |
| Screws & Lockwashers | Material    | Steel                              | Steel                                                        | QQS-630-637    |
|                      | Finish      | Cadmium Plate                      | Cadmium plate                                                | QQ-P-416       |
| Seals                | Material    | N/A                                | Silicone                                                     | N/A            |

How to Order

DPXA/DPXB

DPX A 32C2 - 34 P - 1  
DPX B R MA - 67 - 33 S - 00 01 - F0

SERIES PREFIX  
SHELL STYLE  
RoHS  
CLASS  
CONTACT ARRANGEMENT  
SHELL TYPE  
CONTACT TYPE  
MODIFICATION  
POLARIZING POSITION  
LESS CONTACTS\*

**SERIES PREFIX**  
DPX - ITT designation

**SHELL STYLE**  
A - Single shell  
B - Polarized ARINC shell

**RoHS version**  
R - RoHS compatible

**CLASS**  
No designator - Solder type  
MA - Crimp type with LITTLE CAESAR contact assembly  
ME - Environmental crimp type  
MB - Wire seperator  
MK - Mounting springs

**CONTACT ARRANGEMENT**  
2 thru 106 (see pages H-50 to H-54)

**SHELL TYPE**  
33 for plug; 34 for receptacle

**CONTACT TYPE**  
P for pin; S for socket

**MODIFICATION**  
DPXA - See page H-66 to H-69  
DPXB - See pages H-66 to H-69.

**POLARIZING POSITION**  
For DPXB shell style only

DPX2

DPX 2 57 P - 57 P - 33 B - 00 01  
DPX 2 MA 57 P - 57 P - 33 A - 03 01  
DPX 2 R MA 57 P - 57 P - 34 B - 02 01 - F0

SERIES PREFIX  
TWO GANG SHELL  
RoHS  
CLASS  
CONTACT ARRANGEMENT  
(Side A)  
CONTACT TYPE  
CONTACT ARRANGEMENT  
(Side B)  
CONTACT TYPE  
SHELL TYPE  
SHELL STYLE  
MODIFICATION NUMBER  
POLARIZING POSITION  
LESS CONTACTS\*

**SERIES PREFIX**  
DPX - ITT Cannon designation

**SHELL**  
2 - Two gang

**RoHS**  
R - RoHS compatible

**CLASS**  
No designator - Solder type  
MA - Crimp type with LITTLE CAESAR contact assembly  
ME - Environmental crimp type

**CONTACT ARRANGEMENT**  
2 thru 106 (see pages H-50 to H-54)

**CONTACT TYPE**  
P for pin; S for socket

**SHELL TYPE**  
33 for plug; 34 for receptacle

**SHELL STYLE**  
No designator - original two-gang DPX  
A - ARINC A shell  
B - ARINC B shell

**MODIFICATION**  
See pages H-66 to H-69.

**POLARIZING POSITION**  
See pages H-70



## How to Order

## DPX3/DPX4

|                     |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
|---------------------|-----|---|----|------|---|------|---|------|---|------|---|------|------|----|
|                     | DPX | 3 | ME | - 57 | P | - 57 | P | - 57 | P | - 57 | P | - 34 | - 00 | 01 |
|                     | DPX | 4 | ME | - 57 | P | - 57 | P | - 57 | P | - 57 | P | - 34 | - 00 | 01 |
| SERIES PREFIX       |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| SHELL               |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CLASS               |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT ARRANGEMENT |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| (Side A)            |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT TYPE        |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT ARRANGEMENT |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| (Side B)            |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT TYPE        |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT ARRANGEMENT |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| (Side C)            |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT TYPE        |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT ARRANGEMENT |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| (Side D)            |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| CONTACT TYPE        |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| SHELL TYPE          |     |   |    |      |   |      |   |      |   |      |   |      |      |    |
| MODIFICATION NUMBER |     |   |    |      |   |      |   |      |   |      |   |      |      |    |

## SERIES PREFIX

DPX - ITT designation

## SHELL

3 - Three gang 4 - Four gang

## CLASS

MA - Crimp type contacts in LITTLE CAESAR  
contact assembly  
ME - Environment- resistant, crimp type contacts

## \*CONTACT ARRANGEMENT

See pages H-50 to H-54 for applicable arrangements.  
Please specify each arrangement number as in-  
dicated in ordering nomenclature for 3 or 4 gang if  
not listed below.

ROHS Finish Zinc Plate per ASTM-B-633 with Trivalent Chromate Coating

## POLARIZING POSITION

## \*\*CONTACT TYPE

P for pin; S for socket. Designation follows each  
arrangement as ordered for 3 or 4 gang versions.

## SHELL TYPE

33 for plug; 34 for receptacle

MODIFICATION See pages H-66 to H-69.

POLARIZING POSITION See pages H-70

## DPXMA/ME

## DPXMA/DPXME - 0PX - 3 Shell Layouts

| Insert - Used in shell position as noted |     |       |       |       |       |       |
|------------------------------------------|-----|-------|-------|-------|-------|-------|
| Layout                                   | MA: | W8    | 32W4  | 57    | 67    | A106  |
|                                          | ME: | AW8   | A32W4 | 57    | 67    | A106  |
| *E24                                     |     | A,B,C |       |       |       |       |
| *F122                                    |     | A,B   |       |       |       | C     |
| G122                                     |     | B     |       | A,C   |       |       |
| *E142                                    |     | C     |       |       | A,B   |       |
| *A166                                    |     |       | C     |       | A,B   |       |
| 171                                      |     |       |       | A,B,C |       |       |
| 201                                      |     |       |       |       | A,B,C |       |
| *C205                                    |     |       | C     |       | A     | B     |
| B240                                     |     |       |       |       | A,C   | B     |
| C240                                     |     |       |       |       | A,B   | C     |
| *D244                                    |     |       | C     |       |       | A,B   |
| A279                                     |     |       |       |       | C     | A,B   |
| A318                                     |     |       |       |       |       | A,B,C |

\*Applicable to "ME" only. Consult factory for similar layouts application to "MA."

NOTE: For pictorial views of above layouts see pages 52-56.



## DPXMA/DPXME - 0PX - 4 Shell Layouts

|        | Insert - Used in shell position as noted |     |       |       |       |         |         |      |
|--------|------------------------------------------|-----|-------|-------|-------|---------|---------|------|
|        | MA:                                      | W8  | 26    | 32W4  | 57    | 67      | A106    | None |
| Layout | ME:                                      | AW8 | 26    | A32W4 | 57    | 67      | A106    | None |
| 145    |                                          |     | A,B,C |       |       | D       |         |      |
| *B148  |                                          | C,D | B     |       |       |         | A       |      |
| B150   |                                          | A,B |       |       | A,C   | C,D     |         |      |
| *181   |                                          | B   |       |       |       | A       | C       | D    |
| *B189  |                                          | C,D |       |       |       | B       | A       |      |
| *A198  |                                          |     |       | C,D   | A,B,C | A,B     |         |      |
| 268    |                                          |     |       |       |       | A,B,C,D |         |      |
| *E287  |                                          | D   |       |       |       | B       | A,C     |      |
| *220   |                                          | B   |       |       |       |         | C,D     | A    |
| *A233  |                                          |     |       | A     |       | B,C,D   |         |      |
| 279    |                                          |     |       |       |       | A       | C,D     | B    |
| *F287  |                                          | B   |       |       |       | A       | C,D     |      |
| *E326  |                                          | B   |       |       |       |         | A,C,D   |      |
| A346   |                                          |     |       |       |       | C,D     | A,B     |      |
| B346   |                                          |     |       |       |       | A,B     | C,D     |      |
| 385    |                                          |     |       |       |       | A       | B,C,D   |      |
| A424   |                                          |     |       |       |       |         | A,B,C,D |      |



## Single Gang

### DPXA-33



All tolerances  $\pm .015(0.38)$  unless otherwise noted.



### DPXA-34





### DPXA-33 ARINC Shell



NOTE: DPXME AND DPXNE GROMMETS ARE APPLICABLE TO ALL SHELL SIZES

### DPXA-34 ARINC Shell




NOTE - ARINC requires that DPXB shells are mounted with the polarizing posts at the top. See pages 71-72

Dimensions shown in inches (mm)  
Specifications and dimensions subject to change




## Two Gang

### DPX2-33 Shell



All tolerance are  $\pm .015$  (0.38) unless otherwise noted.





### DPX2-34 Shell



### DPX2-33A ARINC A Shell




### DPX2-34A ARINC A Shell



Dimensions shown in inches (mm)  
Specifications and dimensions subject to change


## Two Gang - ARINC B Shell

DPX2-33B




DPX2-34B

All tolerances are  $\pm .015(0.38)$  unless other wise noted.




## Two Gang - Screw Coupling


DPX2-33F (Female)




DPX2-34M (Male)



DPX2-34F (Female)




DPX2-33M (Male)




## Engaging Devices

DPX2-34M with wing handle type  
-0901; example, DPX2-34M-0901



DPX2-34M with extended hex,  
knob type -0501; example, DPX2-34M-0501





Not available on DPX2-34B Shells

Two Gang - ARINC B Shell

DPX3-33

DPX3-34



All tolerances are  $\pm .015(0.38)$  unless other wise noted.



Four Gang

DPX4-33

DPX4-34







Contact Arrangement Variations Solder Type (Captive Contacts)

NOTE: See pages 59-60 for Coaxial/Power Contact Termination Data


C2




C7




8\*




10C3\*




B16C3\*




17



23












25C3\*



| Contact Arr. | No. of Contacts & Wire size | Test Voltage AC (RMS)         | PIN               |                         |                   |                 | SOCKET          |                   |                 |
|--------------|-----------------------------|-------------------------------|-------------------|-------------------------|-------------------|-----------------|-----------------|-------------------|-----------------|
|              |                             |                               | Contacts Arr. No. | No. of Contacts         | Contact Type Code | Contact Numbers | No. of Contacts | Contact Type Code | Contact Numbers |
| C2           | 2 coax (RG-9/U)             | 1000 (1,2)V matched impedance | C2                | 2                       | R                 | 1-2             | 2               | R                 | 1-2             |
|              |                             |                               | C2C               | 2                       | AB                | 1-2             | Consult Factory |                   |                 |
|              |                             |                               | C2M               | Consult Factory         |                   |                 | 2               | AC                | 1-2             |
| C7           | 7 coax                      | 1000 (1-7)V                   | C7                | 7                       | K                 | 1-7             | 4               | F                 | 1,2,4,5         |
|              |                             |                               |                   |                         |                   |                 | 3               | G                 | 3,6,7           |
|              |                             |                               | C7A               | 7                       | A                 | 1-7             | Same as Pin     |                   |                 |
|              |                             |                               | C7B               | 7                       | B                 | 1-7             | Same as Pin     |                   |                 |
|              |                             |                               | C7B               | Same as Socket (Use C7) |                   |                 | 7               | K                 | 1-7             |
|              |                             |                               | C7M               | 7                       | C                 | 1-7             | Same as Pin     |                   |                 |
|              |                             |                               | C7X               | 7                       | AA                | 1-7             | Same as Pin     |                   |                 |
|              |                             |                               | C7AA              | 7                       | Z                 | 1-7             | Same as Pin     |                   |                 |
| 8            | 8 #12                       | 2000V                         | 8                 | N                       | 1-8               | 8               | 0               | 1-8               |                 |
| 10C3         | 7 #20 3 coax                | 1500 (1-4, 8-10)V             | 10C3              | 7                       | L                 | 1-4, 8-10       | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | I                 | 5,6,7           |                 |                   |                 |
|              |                             |                               | A10C3             | 7                       | L                 | 1-4, 8-10       | Same as Pin     |                   |                 |
| B16C3        | 13 #16 3 coax               | 1500 (4-16)V 1000 (1-3)V      |                   | 3                       | J                 | 5,6,7           |                 |                   |                 |
|              |                             |                               | B16C3             | 13                      | M                 | 4-16            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | A                 | 1-3             |                 |                   |                 |
|              |                             |                               | C16C3             | 13                      | M                 | 4-16            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | B                 | 1-3             |                 |                   |                 |
|              |                             |                               | G16C3             | 13                      | M                 | 4-16            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | C                 | 1-3             |                 |                   |                 |
|              |                             |                               | J16C3             | 13                      | M                 | 4-16            | Same as Pin     |                   |                 |
| 17           | 17 #20                      | 2000V                         |                   | 3                       | K                 | 1-3             |                 |                   |                 |
|              |                             |                               |                   | 3                       | Z                 | 1-3             |                 |                   |                 |
|              |                             |                               |                   | 3                       | AA                | 1-3             |                 |                   |                 |
|              |                             |                               | ZF16C3            | 13                      | M                 | 4-16            | Same as Pin     |                   |                 |
| 23           | 23 #20                      | 2000 (15-23). 1500 (1-14)V.   | 23                | 23                      | L                 | 1-23            | Same as Pin     |                   |                 |
| 25C3         | 22 (#20). 3 coax            | 1500 (4-25)V. 1000 (1-3)V     | 25C3              | 22                      | L                 | 4-25            | 22              | L                 | 4-25            |
|              |                             |                               |                   | 3                       | K                 | 1-3             | 2               | F                 | 1,3             |
|              |                             |                               |                   |                         |                   |                 | 1               | G                 | 2               |
|              |                             |                               | F25C3             | 22                      | L                 | 4-25            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | C                 | 1-3             |                 |                   |                 |
|              |                             |                               | G25C3             | 22                      | L                 | 4-25            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | A                 | 1-3             |                 |                   |                 |
|              |                             |                               | J25C3             | 22                      | L                 | 4-25            | Same as Pin     |                   |                 |
| 25C3         |                             |                               |                   | 3                       | B                 | 1-3             |                 |                   |                 |
|              |                             |                               | Q25C3             | 22                      | L                 | 4-25            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | Z                 | 1-3             |                 |                   |                 |
| 25C3         |                             |                               | R25C3             | 22                      | L                 | 4-25            | Same as Pin     |                   |                 |
|              |                             |                               |                   | 3                       | AA                | 1-3             |                 |                   |                 |

## Contact Arrangement Variations Solder Type (Captive Contacts)

NOTE: See pages 59-60 for Coaxial/Power Contact Termination Data










|       | Contact Arr.                                                                        | No. of Contacts & Wire Size  | Test Voltage AC (RMS)                     | Contact Arr. No. | PIN             |                   | SOCKET                          |                 |                   |
|-------|-------------------------------------------------------------------------------------|------------------------------|-------------------------------------------|------------------|-----------------|-------------------|---------------------------------|-----------------|-------------------|
|       |                                                                                     |                              |                                           |                  | No. of Contacts | Contact Type Code | Contact Numbers                 | No. of Contacts | Contact Type Code |
| 26*   |    |                              |                                           | 26               | 26              | M                 | 1-26                            |                 | Same as Pin       |
| 30C4  |    | 15 #20,<br>11 #16,<br>4 coax | 1500 (2-5 & 7-13)V<br>1000 (1,6 & 14-26)V | A30C4            | 15<br>11<br>4   | L<br>M<br>Z       | 1,6 14-26<br>2-5, 7-13<br>27-30 |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | B30C4            | 15<br>11<br>4   | L<br>M<br>AA      | 1,6 14-26<br>2-5, 7-13<br>27-30 |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | C30C4            | 15<br>11<br>4   | L<br>M<br>A       | 1,6 14-26<br>2-5, 7-13<br>27-30 |                 | Same as Pin       |
| 32    |    | 3 #16<br>29 #20              | 2000 (1-6)<br>1500 (7-32)V                | 32               | 29<br>3         | L<br>M            | 1,3,4,7-32<br>2,5,6             |                 | Same as Pin       |
| 32C2* |    | 30 #20<br>2 coax             | 1500 (1-30)V<br>1000 (A1, A2)V            | 32C2             | 30<br>2         | L<br>K            | 1-30<br>A1, A2                  | 30<br>2         | L<br>F            |
|       |                                                                                     |                              |                                           | A32C2            | 30<br>2         | L<br>A            | 1-30<br>A1, A2                  |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | C32C2            | 30<br>2         | L<br>B            | 1-30<br>A1, A2                  |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | D32C2            | 30<br>2         | L<br>C            | 1-30<br>A1, A2                  |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | M32C2            | 30<br>2         | L<br>Z            | 1-30<br>A1, A2                  |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | N32C2            | 30<br>2         | L<br>AA           | 1-30<br>A1, A2                  |                 | Same as Pin       |
| 40*   |  | 40 #20                       | 1500V                                     | 40               | 40              | L                 | 1-40                            |                 | Same as Pin       |
| 40C1* |  | 39 #20<br>1 coax             | 1500 (1-39)V<br>1000 (A1)V                | 40C1             | 39<br>1         | L<br>B            | 1-39<br>A1                      |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | A40C1            | 39<br>1         | L<br>K            | 1-39<br>A1                      | 39<br>1         | L<br>F            |
|       |                                                                                     |                              |                                           | F40C1            | 39<br>1         | L<br>C            | 1-39<br>A1                      |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | J40C1            | 39<br>1         | L<br>Z            | 1-39<br>A1                      |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | K40C1            | 39<br>1         | L<br>AA           | 1-39<br>A1                      |                 | Same as Pin       |
|       |                                                                                     |                              |                                           | L40C1            | 39<br>1         | L<br>A            | 1-39<br>A1                      |                 | Same as Pin       |
| 45*   |  | 45 #20                       | 1500V                                     | 45               | 45              | L                 | 1-45                            |                 | Same as Pin       |
| 57*   |  | 57 #20                       | 1500V                                     | 57               | 57              | L                 | 1-57                            |                 | Same as Pin       |
| 67*   |  | 64 #20<br>3 #16              | 1000V                                     | 67               | 64<br>3         | L<br>M            | 1-2,6-65<br>3-5                 |                 | Same as Pin       |

Dimensions shown in inches (mm)  
Specifications and dimensions subject to change

www.ittcannon.com

Contact Arrangement Variations, Crimp Type - DPX\*MA/ME Series

NOTE: See pages 62-65 for Coaxial Contact data  
See pages 57-58 for Crimp Contact data

|         | Contact Arr.                                                                        | No. of Contacts & Wire Size | Test Voltage AC (RMS)                                                             | Contact Arr. No.                             | No. of Contacts                          | Contact Size or Code Letter                       | Contact Numbers            |
|---------|-------------------------------------------------------------------------------------|-----------------------------|-----------------------------------------------------------------------------------|----------------------------------------------|------------------------------------------|---------------------------------------------------|----------------------------|
| 8       |    | 8 #12                       |                                                                                   | 8                                            | 8                                        | 12                                                | 1-8                        |
| D8      |    | 4 #16, 4 #12                |                                                                                   | D8                                           | 4                                        | 16<br>12                                          | 1-4<br>5-8                 |
| W8**    |    | 8 coax                      | 1000V (1-8)V                                                                      | W8<br>C8A<br>C8B<br>C8C<br>C8E<br>C8G<br>C8H | 8                                        | coax<br>G<br>F<br>H<br>R<br>S<br>AB               | 1-8                        |
| 10      |    | 2 #8, 8 #20                 | 1500V                                                                             | 10                                           | 2<br>8                                   | B<br>20                                           | 1,2<br>3-10                |
| A10     |   | 8 #16, 2 #4                 | 1500V                                                                             | A10                                          | 8<br>2                                   | 16<br>4                                           | 1-3, 5,<br>6, 8-10<br>4, 7 |
| 10W3**  |  | 7 #20, H.D.,<br>3 coax      | 1500<br>(1-4, 8-10)V                                                              | 10W3<br>A10C3<br>B10C3                       | 7<br>3<br>7<br>3<br>7<br>3               | 20 H.D.<br>coax<br>20 H.D.<br>AC<br>20 H.D.<br>AC | 1-4, 8-10<br>5-7           |
| B16W3** |  | SOCKET<br>ONLY<br>B16W3     | 1500 (4-16)<br>1000 (1-3)V<br>socket side only<br>(Not available<br>in ME series) | B16W3                                        | 13<br>3                                  | 16<br>coax                                        | 4-16<br>1-3                |
| 25W3    |  | 22 (#20) 3 coax             | 1500 (4-25)V,<br>1000 (1-3)V<br>(Not available<br>in ME series)                   | 25W3<br>25A3<br>25B3<br>25D3                 | 22<br>3<br>22<br>3<br>22<br>3<br>22<br>3 | 20<br>coax<br>20<br>C<br>20<br>D<br>20<br>B       | 4-25<br>1-3                |
| 26      |  | 26 #16                      | 1500V                                                                             | 26                                           | 26                                       | 16                                                | 1-26                       |

\*\*Crimp rear release coaxial contacts.



Contact Arrangement Variations, Crimp Type - DPX\*MA/ME Series


NOTE: See pages 62-65 for Coaxial Contact data  
See pages 57-58 for Crimp Contact data

|       |  | Contact Arr. | No. of Contacts & Wire Size | Test Voltage AC (RMS)            | Contact Arr. No. | No. of Contacts | Contact Size or Code Letter | Contact Numbers      |
|-------|--|--------------|-----------------------------|----------------------------------|------------------|-----------------|-----------------------------|----------------------|
| 57    |  | 57           | 57 #20                      | 1500V                            | 57               | 57              | 20                          | 1-57                 |
| 67    |  | 67           | 64 #20 H.D.<br>3 #16        | 1500 (3-5)<br>1000 (1, 2, 6-67)V | 67               | 64<br>3         | 20 H.D.<br>16               | 1-2, 6-67<br>3, 4, 5 |
| A106† |  | A106†        | 106 #22                     | 1000V                            | A106             | 106             | 22                          | 1-106                |

\*\*Crimp rear release coaxial contacts.  
†A106 arrangements have the POS-ALINE connector design. See below.  
NOTE: Engaging force of each layout arrangement shall not exceed 45 lbs. maximum.

Positive Contact Alignment Design

For high density A106 contact arrangement



In the POS-ALIGN connector construction the entire pin contact is recessed in an individual cavity in the plug insulator while the sturdy socket members are exposed and extend from the connector receptacle face. There is a lead-in chamfer that guides the socket contact into the pin cavity assuring proper contact alignment during mating and protecting the pin contact from damage and wear.

Rear inserstion, release and extraction of crimp snap-in contacts

The ITT Cannon LITTLE CAESAR contact assembly permits contacts to be inserted, released, and extracted from the rear of the connector with a simply, expendable plastic tool.  
The contact is inserted from the rear of the connector thru a cylindrical clip in the insulator until indented tines of the clip snap securely behind the contact shoulder. The contact is released as the plastic tool is inserted into the rear of the connector, expanding the tines beyond the contact shoulder, permitting contact extraction. The simplified contact design has a single holding shoulder and no undercuts for improved bend resistance.  
Other features of the LITTLE CAESAR contact assembly include: hard dielectric socket face with lead-in chamfers for positive mating of contacts; good contact stability with minimum clearance between the contact and the insulator cavity wall; plus a "closed-down" design of the insulator's hard dielectric around each pin contact.  
This LITTLE CAESAR contact assembly was selected by the National Aerospace Standards Committee as the system to be used in a major industry connector specification, for vital programs demanding great operational reliability.  
The LITTLE CAESAR contact assembly is currently available in the BKA, DPX\*MA, DPK, DPDMA, and DPAMA Series.

## Contact and Termination Tooling Data - Commercial

## Crimp Contacts

The crimp contacts are shipped with the connector, not installed. Additional contacts may be ordered using the part numbers listed below. All tools must

be purchased separately. The insertion/extraction tools listed are plastic type. Consult factory for more durable metal tools.

|                 |        | Part Number          |                      |  | Wire<br>Accom. | Crimp<br>Tool<br>Part<br>Number       | Locator<br>Part<br>Number                                  | Insertion/<br>Extraction<br>Tool<br>(Part No.) | Layout Usage                            |                                               |
|-----------------|--------|----------------------|----------------------|--|----------------|---------------------------------------|------------------------------------------------------------|------------------------------------------------|-----------------------------------------|-----------------------------------------------|
| Contact<br>Size | Type   | DPX MA<br>Commercial | DPX ME<br>Commercial |  |                |                                       |                                                            |                                                | DPX<br>ME                               | DPX<br>MA                                     |
| 2222            | Pin    | 030-1975-007         | 030-1975-005         |  | 22,24,26       | M22520/2-01                           | M22520/2-23                                                | CIT-DPXMA-22<br>M81969/1-01                    | A106                                    | A106                                          |
|                 | Socket | 031-1113-007         | 031-1113-008         |  |                |                                       |                                                            |                                                |                                         |                                               |
| 2020            | Pin    | 030-9081-000         | 030-2040-000         |  | 20,22,24       | M22520/2-01<br>MS-3191-1<br>MS-3191-3 | M22520/2-02<br>Std. Locator<br>Std. Locator<br>M22520/2-01 | CIET-20<br>(274-7001-000)                      | 10,<br>A32W2,<br>40,<br>A40W1,<br>45,57 | 10,<br>25W2,<br>32W2<br>40,<br>40W1,<br>45,57 |
|                 | Socket | 031-9134-001         | 031-1046-002         |  |                |                                       |                                                            |                                                |                                         |                                               |
| 2020HD          | Pin    | 030-9081-003         | 030-1892-002         |  | 20,22,24       | M22520/2-01<br>MS-3191-1              | M22520/2-08<br>Standard                                    | CIET-20<br>M81969/1-02<br>(980-0004-805)       | 10W3<br>A32W4,<br>67                    | 10W3<br>32W4,<br>67                           |
|                 | Socket | 031-9134-004         | 031-1047-002         |  |                |                                       |                                                            |                                                |                                         |                                               |
| 1616            | Pin    | 030-9083-001         | 030-1893-002         |  | 16,18,20       | M22520/1-01<br>MS-3191-1              | M22520/1-02<br>Std. Locator                                | CIET-16<br>(274-7002-000)                      | D8,<br>A10,<br>26,<br>A32W4,<br>67      | D8,<br>A10,<br>B16W3,<br>26,<br>32W4,<br>67   |
|                 | Socket | 031-9206-004         | 031-9206-021         |  |                |                                       |                                                            |                                                |                                         |                                               |
| 1212            | Pin    | 030-1909-001         | 030-2045-000         |  | 12,14          | M22520/1-01                           | M22520/1-11                                                | CIET-12<br>(274-7003-000)                      | D8                                      | 8,<br>D8                                      |
|                 | Socket | 031-1059-001         | 031-1059-002         |  |                |                                       |                                                            |                                                |                                         |                                               |
| 0808            | Pin    | 030-1908-001         | 030-1908-001         |  | 8              | CBT-600*<br>CBT600B*                  | CCH8-1 Head<br>CCHP-8-6                                    | CET-8-2<br>(323-7004-000)                      | 10                                      | 10                                            |
|                 | Socket | 031-1154-000         | 031-1154-000         |  |                |                                       |                                                            |                                                |                                         |                                               |
| 0406            | Pin    | 030-2049-000         | 030-2049-000         |  | 6              | CBT-600*<br>CBT600B*                  | CCH4-1 Head<br>CCHP-4-8                                    | CET-4-8<br>(323-7008-000)                      | A10                                     | A10                                           |
|                 | Socket | 031-1151-000         | 031-1151-000         |  |                |                                       |                                                            |                                                |                                         |                                               |

\* Requires air line pressure of 80 to 100 psi.

These DPXME contacts are being superseded in favor of military DPXNE/NA contacts, this applies to all existing DPXME connector assemblies, except for size 20 contacts.

## Electrical Data

| Contact<br>Size | Wire<br>Size | Insulation (O.D.)<br>Limits Inch (mm)<br>Max. | Test Current<br>per MIL-C-39029<br>Table VI | Max. Current for<br>Tests (Amps)<br>(Mil-C-39029) | Max. Potential Drop<br>(Millivolts)<br>at 25°C<br>per MIL-C-39029 |
|-----------------|--------------|-----------------------------------------------|---------------------------------------------|---------------------------------------------------|-------------------------------------------------------------------|
| 4               | 6            | .310 (7.87)                                   | 60                                          | 60                                                | 33                                                                |
| 8               | 8            | .250 (6.35)                                   | 46                                          | 46                                                | 39                                                                |
| 12              | 12           | .135 (3.43)                                   | 23                                          | 23                                                | 63                                                                |
|                 | 14           |                                               | 17                                          | 17                                                | 60                                                                |
| 16              | 16           | .103 (2.62)                                   | 13                                          | 13                                                | 68                                                                |
|                 | 18           |                                               | -                                           | -                                                 | -                                                                 |
|                 | 20           |                                               | 7.5                                         | -                                                 | 75                                                                |
| 20              | 20           | .071 (1.80)                                   | 7.5                                         | 7.5                                               | 83                                                                |
|                 | 22           |                                               | -                                           | -                                                 | -                                                                 |
|                 | 24           |                                               | 3                                           | 3.0                                               | 68                                                                |
| 22              | 22           | .054 (1.37)                                   | 5                                           | 5.0                                               | 110                                                               |
|                 | 24           |                                               | -                                           | -                                                 | -                                                                 |
|                 | 26           |                                               | 2                                           | 2.0                                               | 80                                                                |

Description of Modification Codes for Special Connector Insert Assemblies

| Class | Series           | DPX Insert Type                                                                   | Class   | Series | DPX Insert Type                                                                                      | Class                      | Series | DPX Insert Type                                                                                                      |
|-------|------------------|-----------------------------------------------------------------------------------|---------|--------|------------------------------------------------------------------------------------------------------|----------------------------|--------|----------------------------------------------------------------------------------------------------------------------|
| None  | DPXA<br>DPXB     | Two (2) pieces, solder pot.                                                       | D*      | -      | (MA) LITTLE CAESAR assembly, crimp pot, (Cat. A)                                                     | DPX2CA-I                   | -      | A side: (MAS) LITTLE CAESAR assembly, solder pot (32W2S)                                                             |
| MA    | DPXAMA<br>DPXBMA | LITTLE CAESAR rear release contact retention assembly, crimp pot.                 | E*      | -      | Metal plates.                                                                                        | DPX2AC-<br>(Reverse<br>CA) | -      | B side: Standard 2 Piece, solder pot (57S).<br>Ex: DPX2CA-32W2S57S-33-0001                                           |
| MAS   | -                | LITTLE CAESAR assembly, solder pot,                                               | F*      | -      | Rear release, crimp (MB type only).                                                                  | DPX2AF                     | -      | A side: Standard solder pot.<br>B side: Rear release crimp with separator.<br>Ex: DPX2AF-13S26S-33B-0001             |
| MB    | -                | LITTLE CAESAR rear release contact retention assembly, crimp pot, with separator. | DPX2-   | -      | Standard 2 pieces, solder pot, both sides,<br>Ex: DPX2-57S57S-33-0001                                | DPX2BA                     | -      | A side: Ring-Loc solder pot (40W1S).<br>B Side: 2 Piece, Solder Pot (57S).<br>Ex: DPX2BA-40W1S57S-33-0001            |
| MS    | -                | Ring-Loc, solder pot,                                                             | DPX2MA  | -      | Standard LITTLE CAESAR assembly, crimp pot both sides Ring-loc coax.<br>EX:DPX2MA-57S57S-33-0001     | DPX2DA                     | -      | A side: (MA) LITTLE CAESAR assembly, Crimp (67S).<br>B Side: 2 Piece, solder pot (57S).<br>Ex: DPX3DA-67S57S-33-0001 |
| ME    | -                | Environmental, connector.                                                         | DPX2MAS | -      | LITTLE CAESAR assembly, solder po, both sides Ring-Loc coax.<br>EX: DPX2MAS-57S57S-33-0001           | DPX2EB                     | -      | A side: Metal plates for grounding (Coaxes).<br>B side: Ring-Loc, solder pot.<br>Ex: DPX2EB-C1P40W1P-34B-0001        |
| A*    | -                | Two (2) pieces, solder pot (Standard 2 pieces insert).                            | DPX2MS- | -      | Ring-Loc, solder pot. Layout 25C3 pin only and 40C1 Pin and socket.<br>EX: DPX2MS-40W1S40W1S-33-0001 |                            |        |                                                                                                                      |
| B*    | -                | Ring-Loc, solder pot. (See MS)                                                    |         |        |                                                                                                      |                            |        |                                                                                                                      |
| C*    | -                | (MAS) LITTLE CAESAR assembly, Solder pot.                                         |         |        |                                                                                                      |                            |        |                                                                                                                      |

\*NOTE: When any two of these letters are used in combination, the inserts ("A" and "B") side have the style contacts indicated (see table opposite for examples).

Contact and Termination Tooling Data

DPXMA (LIF) Crimp Contacts

| Contact Size and Part Numbers      |              |              | Crimp Tooling   |                  |                    |                 |                  |                  | Insertion/ Extraction Tooling            |                                        |                                      |                | Wire Size          |                          |
|------------------------------------|--------------|--------------|-----------------|------------------|--------------------|-----------------|------------------|------------------|------------------------------------------|----------------------------------------|--------------------------------------|----------------|--------------------|--------------------------|
| Part Number                        |              |              | Tool P/N        |                  | Se-<br>lec<br>tor# | Locator P/N     |                  | MIL<br>Spec      | ITT Cannon                               |                                        |                                      | AWG            | Insul<br>Dia. Max. | Strip<br>Length          |
| Size                               | Pin          | Socket       | MIL<br>Spec     | ITT<br>Cannon    |                    | MIL<br>Spec     | ITT<br>Cannon    |                  | Insertion                                | Extraction                             | Ins./Ext.                            |                |                    |                          |
| 222                                | 030-2259-000 | 031-1287-000 | M22520<br>/2-01 | 995-0001<br>-584 | 3<br>3<br>4        | M22520<br>2-23  | 995-0002<br>-015 | M81969<br>/1-01  | CIT-DPXMA-22-1<br>Metal<br>(070256-0000) | CET-DPXMA-22<br>Metal<br>(070317-0000) | (980-0004-804)<br>Metal Tip          | 26<br>24<br>22 | .054<br>(1.37)     | .130/.110<br>(3.30/2.54) |
| 2020HD                             | 030-2273-000 | 031-1302-000 | M22520<br>/2-01 | 995-0001<br>-584 | 6<br>7             | M22520<br>/2-08 | 995-0001<br>-604 | M81969<br>/1-02  | -                                        | -                                      | (980-0004-805)<br>Metal Tip          | 22<br>20       | .071<br>(1.80)     | .167/.147<br>(4.24/3.73) |
| 1616                               | 030-2280-000 | 031-1303-000 | M22520<br>1-01  | 995-0001<br>-585 | 4<br>5<br>6        | M22520<br>/1-02 | 995-0001<br>-736 | M81969<br>/1-03  | -                                        | CET-16-9<br>Plastic<br>(323-7001-000)  | (980-0004-806)<br>Metal Tip          | 20<br>18<br>16 | .103<br>(2.62)     | .270/.230<br>(6.86/5.84) |
| 1212                               | 030-2286-000 | 031-1308-000 | M22520<br>1-01  | 995-0001<br>-585 | 7<br>8             | M22520<br>/1-11 | 995-0002<br>-027 | M81969<br>/14-04 | -                                        | CET-12-4<br>Plastic<br>(323-7002-000)  | CIET-12<br>Plastic<br>(274-7003-000) | 14<br>12       | .135<br>(3.43)     | .270/.230<br>(6.86/5.84) |
| N Type Thermocouple NICROSIL-NISIL |              |              |                 |                  |                    |                 |                  |                  |                                          |                                        |                                      |                |                    |                          |












DPXMA Thermocouple Contacts

| Contact Size and Part Numbers |              |              | Crimp Tooling   |                  |                    |                 |                  |                 | Insertion/<br>Extraction Tooling         |                                        |                             | Wire Size      |                    |                          |
|-------------------------------|--------------|--------------|-----------------|------------------|--------------------|-----------------|------------------|-----------------|------------------------------------------|----------------------------------------|-----------------------------|----------------|--------------------|--------------------------|
| Part Number                   |              |              | Tool P/N        |                  | Se-<br>lec<br>tor# | Locator P/N     |                  | MIL<br>Spec     | ITT Cannon                               |                                        |                             | AWG            | Insul<br>Dia. Max. | Strip<br>Length          |
| Size                          | Pin          | Socket       | MIL<br>Spec     | ITT<br>Cannon    |                    | MIL<br>Spec     | ITT<br>Cannon    |                 | Insertion                                | Extraction                             | Ins./Ext.                   |                |                    |                          |
| 2222<br>Alumel                | 030-1975-009 | 031-1113-009 | M22520<br>/2-01 | 995-0001<br>-584 | 3                  | M22520<br>/2-23 | 995-0002<br>-015 | M81969<br>/1-01 | CIT-DPXMA-22-1<br>Metal<br>(070256-0000) | CET-DPXMA-22<br>Metal<br>(070317-0000) | (980-0004-804)<br>Metal Tip | 26             | .054<br>(1.37)     | .130/110<br>(3.30/2.54)  |
| 2222<br>Chromel               | 030-1975-010 | 031-1113-010 |                 |                  | 4                  |                 |                  |                 |                                          |                                        |                             | 7              |                    |                          |
| 20HD<br>Chromel               | 030-2163-000 | 031-1243-000 | M22520<br>/2-01 | 995-0001<br>-584 | 6<br>7             | M22520<br>/2-08 | 995-0001<br>-604 | M81969<br>/1-02 | -                                        | -                                      | (980-0004-805)<br>Metal Tip | 22<br>20       | .071<br>(1.80)     | .167/.147<br>(4.24/3.73) |
| 20HD<br>Alumel                | 030-2162-000 | 031-1242-000 | M22520<br>/2-01 | 995-0001<br>-584 | 6<br>7             | M22520<br>/2-08 | 995-0001<br>-604 | M81969<br>/1-02 | -                                        | -                                      | (980-0004-805)<br>Metal Tip | 22<br>20       | .071<br>(1.80)     | .167/.147<br>(4.24/3.73) |
| 1616<br>Chromel               | 030-1898-000 | 031-1035-000 | M22520<br>1-01  | 995-0001<br>-585 | 4<br>5<br>6        | M22520<br>/1-02 | 995-0001<br>-736 | M81969<br>/1-03 | -                                        | CET-16-9<br>Plastic<br>(323-7001-000)  | (980-0004-806)<br>Metal Tip | 20<br>18<br>16 | .103<br>(2.62)     | .270/.230<br>(6.86/5.84) |
| 1616<br>Alumel                | 030-1897-000 | 031-1034-000 | M22520<br>1-01  | 995-0001<br>-585 | 4<br>5<br>6        | M22520<br>/1-02 | 995-0001<br>-736 | M81969<br>/1-03 | -                                        | CET-16-9<br>Plastic<br>(323-7001-000)  | (980-0004-806)<br>Metal Tip | 20<br>18<br>16 | .103<br>(2.62)     | .270/.230<br>(6.86/5.84) |
| 1616<br>Constantan            | 030-1905-000 | 031-1061-000 | M22520<br>1-01  | 995-0001<br>-585 | 4<br>5<br>6        | M22520<br>/1-02 | 995-0001<br>-736 | M81969<br>/1-03 | -                                        | CET-16-9<br>Plastic<br>(323-7001-000)  | (980-0004-806)<br>Metal Tip | 20<br>18<br>16 | .103<br>(2.62)     | .270/.230<br>(6.86/5.84) |
| 1616<br>Constantan            | 030-1904-000 | 031-1060-000 | M22520<br>1-01  | 995-0001<br>-585 | 4<br>5<br>6        | M22520<br>/1-02 | 995-0001<br>-736 | M81969<br>/1-03 | -                                        | CET-16-9<br>Plastic<br>(323-7001-000)  | (980-0004-806)<br>Metal Tip | 20<br>18<br>16 | .103<br>(2.62)     | .270/.230<br>(6.86/5.84) |

See DPXMA contact for standard size 20 thermocouple contacts



## Coaxial/Power Contact Termination Data (Retained by Captive Insulator Assy.)






| Rear Extension<br>from insulator                                                    | Contact<br>type<br>code | Part Number                                  |                                              | Cable<br>Accommodation         | Layout<br>Accommodation                      |
|-------------------------------------------------------------------------------------|-------------------------|----------------------------------------------|----------------------------------------------|--------------------------------|----------------------------------------------|
|                                                                                     |                         | Pin                                          | Socket                                       |                                |                                              |
|     | <b>A</b>                | 249-0672-000                                 | 249-0671-000                                 | RG-187/U<br>RG-188/U           | C7A, B16C3,<br>G25C3, C30C4,<br>A32C2, L40C1 |
|     | <b>B</b>                | 249-0702-000                                 | 249-0703-000                                 | RG-180/U<br>RG-195/U           | C7B, J25C3,<br>C16C3, C32C2,<br>40C1         |
|     | <b>C</b>                | 249-0749-000                                 | 249-0750-000                                 | RG-55/U<br>RG-58/U<br>RG-223/U | C7H, G16C3,<br>F25C3, D32C2,<br>F40C1        |
|     | <b>D</b>                | -                                            | 249-0518-000                                 | RG-59/U                        | C7J, H16C3,<br>H25C3, F32C2,<br>E30C4, E40C1 |
|   | <b>I</b>                | 249-0365-000                                 | 249-0353-000                                 | RG-7/U                         | 10C3                                         |
|  | <b>J</b>                | 249-0257-000                                 | 249-0268-000                                 | RG-55/U<br>RG-58/U<br>RG-223/U | A10C3                                        |
|  | <b>K</b>                | 249-0583-000<br>024-0015-000<br>253-0120-000 | 249-0591-000<br>024-0015-000<br>253-0120-000 | RG-187/U<br>RG-188/U           | 25C3, 32C2,<br>J16C3, A40C1,<br>C7, C7D      |
|                                                                                     |                         |                                              |                                              |                                | A40C1 pin only, use C40C1 for socket         |
|  | <b>L</b>                | 330-0144-000                                 | 330-0145-000                                 | 7.5 amp #20 wire               | See Note 1                                   |
|  | <b>M</b>                | 030-0056-010                                 | 031-0016-008                                 | 13 amp #16 wire                | See Note 2                                   |
|  | <b>N</b>                | 030-0017-015                                 | -                                            | 23 amp                         | 8                                            |
|  | <b>O</b>                | -                                            | 031-0059-008                                 | #12 wire                       | 8                                            |

\* These coaxial contacts are supplied with the connector.

Dimensions shown in inches (mm)  
Specifications and dimensions subject to change


www.itccannon.com

Coaxial/Power Contact Termination Data (Retained by Captive Insulator Assy.)

| Rear Extension<br>from insulator                                                    | Contact<br>type<br>code | Part Number     |              | Cable<br>Accommodation              | Layout<br>Accommodation                       |
|-------------------------------------------------------------------------------------|-------------------------|-----------------|--------------|-------------------------------------|-----------------------------------------------|
|                                                                                     |                         | Pin             | Socket       |                                     |                                               |
|    | R                       | 249-1521-000    | 249-1522-000 | RG-9/U, RG-214/U                    | C2                                            |
|    | Z                       | 249-1624-000    | 249-1598-000 | RG-58/U<br>with Captive<br>Contact  | C7AA, ZE16C3<br>Q25C3, A30C4<br>M32C2, J40C1  |
|    | AA                      | 249-1599-000    | 249-1622-000 | RG-196/U<br>with Captive<br>Contact | C7X, ZF16C3,<br>R25C3, B30C4,<br>N32C2, K40C1 |
|    | AB                      | 249-1554-000    | 249-1822-000 | RG-58/U                             | C2C                                           |
|  | AC                      | Consult Factory | 249-5027-001 | RG-9/U<br>RG-214/U                  | C2M                                           |

NOTES: 1. Code L-10C3, A10C3, 17, 23, 25C3, E25C3, F25C3, G25C3, H25C3, J25C3, Q25C3, R125C3, 30C4, A30C4, C30C4, D30C4, E30C4, 32, 32C2, A32C2, C32C2, 032C2, F32C2, M32C2, N32C2, Q32C2, 40, 40C1, B40C1, D40C1, E40C1, F40C1, H40C1, J40C1, K40C1, L40C1, 45, 57, 67,  
2. Code M-B16C3, C16C3, G16C3, H16C3, M16C3, ZE16C3, ZF16C3, 26, 30C4, 32, 67

Suggested Cable Trim Dimensions



| Code Letter | Inches    |           |           | Millimeters |             |             |
|-------------|-----------|-----------|-----------|-------------|-------------|-------------|
|             | A         | B         | C         | A           | B           | C           |
| A           | .166/.146 | .358/.318 | .14       | 4.22/3.71   | 9.08/8.08   | 3.55        |
| B           | .166/.146 | .358/.318 | .14       | 4.22/3.71   | 9.08/8.08   | 3.55        |
| C           | .166/.146 | .358/.318 | .14       | 4.22/3.71   | 9.08/8.08   | 3.55        |
| D           | .166/.146 | .358/.318 | .14       | 4.22/3.71   | 9.08/8.08   | 3.55        |
| E           | .166/.146 | .358/.318 | .14       | 4.22/3.71   | 9.08/8.08   | 3.55        |
| I           | .166/.146 | .39       | .166/.146 | 4.22/3.71   | 9.91        | 4.21/3.71   |
| J           | .166/.146 | .55       | .166/.146 | 4.22/3.71   | 13.97       | 4.21/3.71   |
| K           | .198/.178 | .488/.428 | .25       | 5.03/4.52   | 11.38/10.87 | 6.35        |
| Z           | .08       | .41       | .23       | 2.03        | 10.41       | 5.84        |
| AA          | .11       | .23       | .195/.175 | 2.79        | 5.84        | 4.95/4.45   |
| AB          | .238/.198 | .233/.193 | .447/.427 | 6.04/5.03   | 5.92/4.90   | 11.35/10.89 |
| AC          | .345/.281 | .516/.484 | .359/.296 | 8.71/7.14   | 13.1/12.3   | 9.12/7.52   |
| R           | .238/.198 | .233/.193 | .582/.542 | 6.05/5.03   | 5.92/4.90   | 14.8/13.8   |

## Coaxial Cable Assembly


ITT Cannon recommends resistance soldering for all solder contacts, particularly for RF cable where excessive heat will damage the dielectric. Wires

should be pre-tinned. Bushing, endbells, and junction shells (where applicable) must be slipped over wire bundles before soldering is started. Consult


factory for types not shown. The mechanical steps in wiring coaxials described below.

**For Codes A, B, C, D, and E**


1. Cut cable evenly. Trim to dimensions as shown on page 60. Care should be taken not to injure the conductor or dielectric.
2. Remove inner contact from coaxial assembly and solder it to inner conductor of cable.
3. Push inner contact back into coaxial assembly.
4. Pull outer conductor over coaxial shell, and solder.
5. Apply shrink sleeving after assembly.

**For Codes I and J**


1. Cut cable evenly. Trim to dimensions as shown on page 60. Care should be taken not to injure the conductor or dielectric.
2. Comb braid, tin conductor and remove flux.
3. Remove solder pot cover. Insert cable and solder conductor to contact. The dielectric should butt against contact solder pot.
4. Replace solder pot cover and solder braid to ferrule.
5. Apply shrink sleeving after assembly.

**For Codes K**

1. Cut cable evenly. Trim to dimensions as shown on page 60. Care should be taken not to injure the conductor or dielectric.
2. Unscrew cap and remove spacer and inner contact from coaxial assembly.
3. Push cable through center of cap and spacer.
4. Solder inner contact to inner conductor of cable.
5. Push inner contact back into coaxial shell assembly and attach cap.
6. Separate outer conductor of cables into two pigtailed 180° apart.
7. Attach on pigtail to each end of cap strip and solder.
8. Apply shrink sleeving after assembly.

**For Codes Z and AA**


1. Cut cable evenly. Trim to dimensions as shown on page 60. Care should be taken not to injure the conductor or dielectric.
2. Solder inner conductor to coaxial contact through side slot in coaxial with outer sleeve pushed back on cable.
3. Pull sleeve forward over braid and solder through holes in sleeve.
4. Solder sleeve to coaxial body.



## Coaxial Contacts

NOTES: 1. The "X" dimension is take from the rear of the shell.  
 2. Codes G and S are inactive for new design. Use codes AD and AE.  
 3. Code AA is designed for installations that have limited space in the terminal area. Use code AG for standard installations.  
 \*P for pin; S for socket.


### Codes A, B, C, D, E, H, P, R



| Arr. Used In                  | Code Letter | Cable Accommodation                   | Part Number*   | Contact Retention | X Max.       | Y Dia.      | Z Dia.      | Crimp Tool              | Extraction Tool          |
|-------------------------------|-------------|---------------------------------------|----------------|-------------------|--------------|-------------|-------------|-------------------------|--------------------------|
| B16W3<br>25W3<br>32W2<br>40W1 | A           | *RG-59/U                              | P-249-1397-000 | Ring Loc          | .760 (19.30) | .158 (4.01) | .275 (6.53) | CA58073                 | CET-C4<br>(038869-0004)  |
|                               |             | RG-62/U                               | S-249-1398-000 |                   |              | .148 (3.76) | .247 (6.27) |                         |                          |
|                               | B           | *RG-58/U                              | P-249-1399-000 | Ring Loc          | .760 (19.30) | .128 (3.25) | .211 (5.36) |                         |                          |
|                               |             |                                       | S-249-1400-000 |                   |              | .118 (3.00) | .201 (5.10) |                         |                          |
|                               | C           | *RG-180/U                             | P-249-1401-000 | Ring Loc          | .760 (19.30) | .128 (3.25) | .166 (4.22) | CCT-HX4-524<br>CCT-408M |                          |
|                               |             | RG-195/U                              | S-249-1402-000 |                   |              | .118 (3.00) | .156 (3.96) |                         |                          |
|                               | D           | RG-174/U, RG-187/U                    | P-249-1403-000 | Ring Loc          | .760 (19.30) | .072 (1.83) | .121 (3.07) |                         |                          |
|                               |             | RG-179/U, RG-188/U                    | S-249-1404-000 |                   |              | .062 (1.57) | .111 (2.82) |                         |                          |
|                               | E           | RG-178/U                              | P-249-1405-000 | Ring Loc          | .760 (19.30) | .072 (1.83) | .091 (2.31) |                         |                          |
|                               |             | RG-196/U                              | S-249-1406-000 |                   |              | .062 (1.57) | .081 (2.06) |                         |                          |
| W8<br>32W4                    | H           | RG-174/U, RG-187/U                    | P-249-1633-000 | LITTLE<br>CAESAR  | .592 (15.04) | .072 (1.83) | .121 (3.07) | CCT-HX4-524<br>CCT-408M | CET-C8<br>(323-7011-000) |
|                               |             | RG-179/U, RG-188/U                    | S-249-1634-000 |                   |              | .062 (1.57) | .111 (2.82) |                         |                          |
| B16W3<br>25W3<br>32W2<br>40W1 | P           | *RG-58/U with nylon braid over jacket | S-249-1608-000 | Ring Loc          | .760 (19.30) | .128 (3.25) | .235 (5.97) | Crimp<br>CA58073        | CET-C4<br>(038869-0004)  |
|                               |             |                                       |                |                   |              | .118 (3.00) | .215 (5.46) |                         |                          |
| W8<br>32W4                    | R           | *RG-178/U                             | P-249-1670-000 | LITTLE<br>CAESAR  | .592 (15.04) | .072 (1.83) | .091 (2.31) | CCT-HX4-524<br>CCT-408M | CET-C8<br>(323-7011-000) |
|                               |             | RG-196/U                              | S-249-1671-000 |                   |              | .062 (1.57) | .081 (2.06) |                         |                          |


**\*IMPORTANT: These coaxials can only be used in the DPX\*MAS or DPX\*MB Connector Series.**

### Codes F, S, T




|            |   |          |                |                  |              |             |             |                        |                          |
|------------|---|----------|----------------|------------------|--------------|-------------|-------------|------------------------|--------------------------|
| W8<br>32W4 | F | RG-59/U  | P-249-1474-000 | LITTLE<br>CAESAR | .775 (19.68) | .158 (4.01) | .238 (6.04) | CA58073<br>CCT-HX3-156 | CET-C8<br>(323-7011-000) |
|            |   | RG-62/U  | S-249-1471-000 |                  |              | .148 (3.76) | .228 (5.79) |                        |                          |
|            | S | RG-55/U  | P-249-1958-000 | LITTLE<br>CAESAR | .592 (15.04) | .130 (3.30) | .238 (6.04) | CA58073<br>CCT-HX3-156 | CET-C8<br>(323-7011-000) |
|            |   | RG-142/U | S-249-1959-000 |                  |              | .120 (3.05) | .228 (5.79) |                        |                          |
|            | T | RG-59/U  | P-249-1960-000 | LITTLE<br>CAESAR | .592 (15.04) | .158 (4.01) | .238 (6.04) |                        |                          |
|            |   | RG-62/U  | S-249-1961-000 |                  |              | .148 (3.76) | .228 (5.79) |                        |                          |

### Codes G



|            |   |         |                |                  |              |             |             |                         |                          |
|------------|---|---------|----------------|------------------|--------------|-------------|-------------|-------------------------|--------------------------|
| W8<br>32W4 | G | RG-58/U | P-249-1631-000 | LITTLE<br>CAESAR | .500 (12.70) | .130 (3.30) | .211 (5.36) | CCT-HX4-524<br>CCT-408M | CET-C8<br>(323-7011-000) |
|            |   |         | S-249-1632-000 |                  |              | .120 (3.05) | .201 (5.10) |                         |                          |


### Codes J



|                               |   |         |                |          |              |             |             |        |                         |
|-------------------------------|---|---------|----------------|----------|--------------|-------------|-------------|--------|-------------------------|
| W16W3<br>25W3<br>32W2<br>40W1 | J | RG-58/U | P-249-1388-000 | Ring Loc | .798 (20.27) | .130 (3.30) | .273 (6.93) | Solder | CET-C4<br>(038869-0004) |
|                               |   |         | S-249-1390-000 |          |              | .120 (3.05) | .263 (6.68) |        |                         |


## Coaxial Contacts

## CODE K




| Arr.<br>Used In               | Code<br>Letter | Cable<br>Accommodation | Part Number*                     | Contact<br>Retention | X<br>Max.    | Y<br>Dia.                  | Z<br>Dia.                  | Crimp Tool | Extraction<br>Tool      |
|-------------------------------|----------------|------------------------|----------------------------------|----------------------|--------------|----------------------------|----------------------------|------------|-------------------------|
| B16W3<br>25W3<br>32W2<br>40W1 | K              | RG-178/U<br>RG-196/U   | P-249-1384-000<br>S-249-1413-000 | Ring Loc             | .906 (23.01) | .045 (1.14)<br>.035 (0.89) | .098 (2.49)<br>.088 (2.24) | Solder     | CET-C4<br>(038869-0004) |

## CODE L




|                               |   |                      |                                  |          |              |                            |                            |        |                         |
|-------------------------------|---|----------------------|----------------------------------|----------|--------------|----------------------------|----------------------------|--------|-------------------------|
| B16W3<br>25W3<br>32W2<br>40W1 | L | RG-178/U<br>RG-196/U | P-249-1386-000<br>S-249-1414-000 | Ring Loc | .518 (13.16) | .045 (1.14)<br>.035 (0.89) | .098 (2.49)<br>.088 (2.24) | Solder | CET-C4<br>(038869-0004) |
|-------------------------------|---|----------------------|----------------------------------|----------|--------------|----------------------------|----------------------------|--------|-------------------------|

## CODE U




|    |   |                                          |                |                  |              |                            |                            |         |                         |
|----|---|------------------------------------------|----------------|------------------|--------------|----------------------------|----------------------------|---------|-------------------------|
| W8 | U | RG-174/U, RG-187/U<br>RG-179/U, RG-188/U | S-249-1883-000 | LITTLE<br>CAESAR | .425 (10.80) | .069 (1.75)<br>.059 (1.50) | .117 (2.97)<br>.107 (2.72) | CCT-C10 | CET-C8<br>(038869-0004) |
|----|---|------------------------------------------|----------------|------------------|--------------|----------------------------|----------------------------|---------|-------------------------|

## CODE V, AC



|      |    |          |                |                  |              |                            |                            |                    |                           |
|------|----|----------|----------------|------------------|--------------|----------------------------|----------------------------|--------------------|---------------------------|
| 10W3 | V  | RG-115/U | P-249-1956-000 | LITTLE<br>CAESAR | .800 (20.32) | .260 (6.60)<br>.254 (6.45) | .356 (9.04)<br>.349 (8.86) | Buchanan<br>612991 | CET 4-8<br>(323-7008-000) |
|      |    |          | S-249-1957-000 |                  |              |                            |                            |                    |                           |
|      | AC | RG-58/U  |                | LITTLE<br>CAESAR | .800 (20.32) | .205 (5.21)<br>.199 (5.05) | .356 (9.04)<br>.349 (8.86) |                    |                           |
|      |    |          | S-249-1977-000 |                  |              |                            |                            |                    |                           |

## CODE AA, AB, AD, AE, AF, AG



|            |    |                                          |                                  |                  |              |                            |                            |                                                                |                          |
|------------|----|------------------------------------------|----------------------------------|------------------|--------------|----------------------------|----------------------------|----------------------------------------------------------------|--------------------------|
| W8<br>32W4 | AA | RG-178/U<br>RG-196/U                     | P-249-1968-000                   | LITTLE<br>CAESAR | .260 (6.60)  | .088 (2.24)<br>.084 (2.13) | .126 (3.20)<br>.122 (3.10) | T & B #WT400<br><br><br><br><br><br><br><br>Daniels<br>HX4-210 | CET-C8<br>(323-7011-000) |
|            | AB | RG-180/U<br>RG-195/U                     | P-249-1982-000<br>S-249-1983-000 |                  |              |                            |                            |                                                                |                          |
|            | AD | RG-58/U                                  | P-249-2017-000<br>S-249-2018-001 |                  |              |                            |                            |                                                                |                          |
|            | AE | RG-142/U                                 | P-249-2019-001<br>S-249-2020-001 | LITTLE<br>CAESAR | .575 (14.60) | .114 (2.90)<br>.104 (2.64) | .168 (4.27)<br>.158 (4.01) |                                                                |                          |
|            | AF | RG-174/U, RG-187/U<br>RG-179/U, RG-188/U | P-249-1633-004<br>S-249-1634-003 |                  |              |                            |                            |                                                                |                          |
|            | AG | RG-178/U<br>RG-196/U                     | P-249-2061-000<br>S-249-2062-001 |                  |              |                            |                            |                                                                |                          |
|            |    |                                          |                                  |                  |              |                            |                            |                                                                |                          |
|            |    |                                          |                                  |                  |              |                            |                            |                                                                |                          |
|            |    |                                          |                                  |                  |              |                            |                            |                                                                |                          |
|            |    |                                          |                                  |                  |              |                            |                            |                                                                |                          |

Dimensions shown in inches (mm)  
Specifications and dimensions subject to change

## DPX\*MA/ME Coaxial Contact Data (for environmental requirements)

### Components/Accessories

NOTE: The A32W2 & A40W1 (Ring Type Retention); AW8 & A32W4 (LITTLE CAESAR Renention) Coaxial Contact arrangements have been redesigned to provide ease of insertion/removal of the coaxial contacts. Sealing is accomplished with the addition of sealing sleeves provided with the coaxial contact assembly.


### RING TYPE RETENTION (A32W2 & A40W1 CONTACT ARRANGEMENTS)

| Part Number*      |                | Cable Accommodation |                | Ins. Dia.<br>Size/Max. | 'A' Trim<br>Dim. | Crimp<br>Tool |
|-------------------|----------------|---------------------|----------------|------------------------|------------------|---------------|
| Without Seal (MA) | Sealed (ME)    | Seal 1              | Seal 2         |                        |                  |               |
| P-249-1397-001    | P-249-1397-002 | X                   | RG59B, RG62A   | .249 (6.32)            | .435 (11.05)     | CA58073       |
| S-249-1398-003    | S-249-1398-002 |                     |                |                        | .415 (10.54)     |               |
| P-249-1399-001    | P-249-1399-002 | RG58B               | X              | .200 (5.08)            | .460 (11.68)     | CA58073       |
| S-249-1400-003    | S-249-1400-002 |                     |                |                        | .440 (11.18)     |               |
| P-249-1401-001    | P-249-1401-002 | RG195               | RG180B         | .158 (4.01)            | .460 (11.68)     | CA58073       |
| S-249-1402-003    | S-249-1402-002 |                     |                |                        | .440 (11.18)     |               |
| P-249-1403-001    | P-249-1403-002 | RG179B              | RG174, RG179B, | .113 (2.87)            | .460 (11.68)     | CCT-406M      |
| S-249-1404-003    | S-249-1404-002 |                     | RG316          |                        | .440 (11.18)     |               |
| P-249-1405-001    | P-249-1405-002 | RG179B, RG196       | X              | .083 (2.11)            | .480 (12.19)     | CCT-406M      |
| S-249-1406-003    | S-249-1406-002 |                     |                |                        | .460 (11.68)     |               |


\*P for pin, S for socket

†Unsealed accommodates both Seal 1 & Seal 2 Cables.

††For use with connectors supplied less grommet ( Code 29\*\*, etc.)




32W2 (MA Version)  
A32W2 (ME Version)



40W1 (MA Version)  
A40W1 (ME Version)

### Cable Trim Dimensions




### Coaxial Contact Assembly Recommendations

(For Codes A, B, C, D, E, J, K, L and P)


- Center contact, rear insulator, crimp ring, support bushing and seal sleeve are packaged separately and shipped with the coaxial assembly.
- Use impact extraction tool no. CET-C4 (038869-0004). An insertion tool is not required. (See Item 4).
- Cable Assembly Instructions
  - If applicable, determine which portion of seal sleeve should be used. If seal 2 is used, cut off seal 1 portion
  - In sequence, place seal sleeve, support bushing and crimp ring over cable jacket.
  - Trim cable per illustration.
  - Place rear insulator over dielectric.
  - Solder innerconductor to center contact.
  - Insert soldered cable firmly into coaxial with shielding over coaxial shell.
  - Pull crimp ring forward until stopped and crimped.
  - Insert coaxial assembly into connector until engaged. Push support bushing into grommet until shoulder rest on tubular extension. Then pull seal sleeve forward until it is snug against grommet.
- To extract coaxial, push back seal sleeve and support bushing. Then push out coaxial from engaging end with CET-C4 (038869-0004) impact tool.
- When crimping with CA58073 crimp tool, care should be taken to avoid flaring the front end of the crimp ring. Place Crimp jaw so that the second tooth of the indentors is over the end of the crimp ring.
- To facilitate extraction of contacts and avoid splaying the length of free cable adjacent to the rear surface of the connector should not be less than 2.000 (50.80).

### WITHOUT SEAL

(For Codes A, B, C, D, E, J, K, L and P)




SOCKET



PIN

### SEALED




## DPX\*MA/ME Coaxial Contact Data (for environmental requirements)


## Components/Accessories

With Seal  
CU 249-0000-047 & -045

Without Seal  
CU 249-0000-044 & -046




32W4\*\* (MA Version)  
A32W4 (ME Version)



W8\*\* (MA Version)  
AW8 (ME Version)

## Cable Trim Dimensions




## LITTLE CAESAR® CONTACT RETENTION (A32W4 &amp; AW8 CONTACT ARRANGEMENTS)

| Part Number*        |                | Cable Accommodation† |               | Ins. Dia. Size/Max. | 'A' Trim Dim. |
|---------------------|----------------|----------------------|---------------|---------------------|---------------|
| Without Seal†† (MA) | Sealed (ME)    | Seal 1               | Seal 2        |                     |               |
| P-249-1633-004      | P-249-1633-003 | RG179                | RG174, RG316, | .111 (2.82)         | .350 (8.89)   |
| S-249-1634-003      | S-249-1634-002 |                      | RG179B        |                     | .330 (8.38)   |
| P-249-1982-000      | P-249-1982-001 | { RG180B             | RG195         | .158 (8.89)         | .260 (6.60)   |
| S-249-1983-000      | S-249-1983-001 |                      |               |                     | .250 (6.35)   |
| P-249-2017-001      | P-249-2017-000 | { RG58C              | X             | .196(4.98)          | .260 (6.60)   |
| S-249-2018-001      | S-249-2018-000 |                      |               |                     | .250 (6.35)   |
| P-249-2019-001      | P-249-2019-000 | { RG142B             | X             | .196 (4.98)         | .260 (6.60)   |
| S-249-2020-001      | S-249-2020-000 |                      |               |                     | .250 (6.35)   |
| P-249-2061-001      | P-249-2061-000 | { RG178B             | X             | .075 (1.90)         | .260 (6.60)   |
| S-249-2062-001      | S-249-2062-000 |                      |               |                     | .250 (6.35)   |

\*P for Pin, S for Socket

Unsealed accommodates both Seal 1 & Seal 2 cables. CU DWGS with seal 249-0000-044 and 249-0000-045



For use with connector supplied less grommet (Code-29\*\*, etc.). CU DWGS without seal 249-0000-047 and 249-0000-046





## Coaxial Contact Assembly and Extraction Recommendations

- Use Crimp Tool No. DIE Y211 (995-0002-249), Tool M22520 / 5-01 (995-0001-761).
- Use extraction tool No. CET-C8. An insertion tool is not required. (See Note 5).
- Center contact, rear insulator, crimp ring, support bushing (not applicable to RG58/RG142 coaxials), seal sleeve, front insulator, shell and ferrule are shipped unassembled in a common container.
- Cable Assembly Instructions:
  - If applicable, determine which portion of seal sleeve should be used. If seal 2 is used, cut off seal 1 portion.
  - In sequence, place seal sleeve, support bushing and crimp ring over cable jacket.
  - Trim cable per illustration.
  - Comb out braid and flare out ends to permit entry of ferrule.
  - Complete termination per illustration. (See below)
- To extract: coaxial, push back seal sleeve and support bushing. Slip cable into extraction tool. Push tool into insert until it contacts coaxial retaining shoulder. Grip both cable and tool with one hand and pull coaxial rearward out of insert cavity.


## WITHOUT SEAL




## SEALED




- To facilitate extraction of contacts and avoid splaying, the length of free cable adjacent to the rear surface of the connector should not be less than 2.000 (50.80).



- Carefully push inner conductor through rear insulator.
- While holding rear insulator firmly against ferrule, trim conductor to .156 (3.96)/.146 (3.71) dimension.
- Place contact over conductor and solder.



- Push ferrule under braid as far as it will go. Trim off braid extending beyond shoulder of ferrule, if necessary.
- While holding ferrule in place pull crimp sleeve forward over braid until it is tight against shoulder of ferrule. Pull firmly against face of ferrule to make sure it is up tight.
- Trim dielectric to the .035 (0.89)/.030 (0.76) dimension.



- Place front insulator over contact and then push assembly into coaxial shell.
- Place parts in jaw of crimp tool. Locate jaws at start of chamfer on crimp sleeve. Press sleeve firmly into coaxial shell and crimp.
- After assembled coaxial is inserted into connector, push support bushing into grommet until shoulder rests on tubular extension. Then pull sealing sleeve forward until it is snug on grommet.

Dimensions shown in inches (mm)  
Specifications and dimensions subject to change


www.ittcannon.com

# Rack and Panel

## Coaxial Cable Assembly Recommendations (Continued)

## For Code V

1. Trim cable to dimensions shown below.
  - A. Push ferrule under braid as far as it will go and press braid down tightly around ferrule.
  - B. Solder ends of braid to ferrule by applying a small amount of solder. Avoid excess solder as it would cause braid to swell up.
  - C. Remove any solder exceeding the .349 (8.86) max. diameter.
  - D. Check the .075 (1.90) max. dielectric extension, retrim if necessary.
3. A. Place rear insulator over dielectric and conductor into contact.
  - B. Solder contact to conductor through access hole.
  - C. Remove excess solder from outside of contact.
4. A. Place front insulator over contact.
  - B. Push parts into coaxial shell.
  - C. While holding parts firmly against stop shoulder in coaxial shell, place jaw of crimp tool at back end of shell and crimp, use Buchanan crimp tool #612991 [.343 (8.71) across hex].




## For Codes AB, AD, AE, AF and AG

Setp 1 - Trim cable as shown.

Step 2 - Flare out ends of braid to permit entry of ferrule.


Step 3 - Complete termination per instructions as shown below.

- a. Push ferrule under braid as far as it will go. Trim off braid extending beyond shoulder of ferrul, if necessary.
- b. While holding ferrule in place pull crimp sleeve forward over braid until it is tight against shoulder on ferrule. Push firmly against face of ferrule to make sure it is up tight.
- c. Trim dielectric to the .035 (0.89)/.030 (0.76) dimension.
- d. Carefully push inner conductor through rear insulator.
- e. While holding rear insulator firmly against ferrule, trim conductor to .156 (3.96)/.146 (3.71) dimension.
- f. Place contact over conductor and solder.
- g. Place front insulator over contact and then push assembly into coaxial shell.
- h. Place parts in jaw of crimp tool. Locate jaws at start of chamfer on crimp sleeve. Press Sleeve firmly into coaxial shell and crimp. Use Daniels crimp tool HX4-210.



## Cable Trim Dimensions

| Code Letter        | Inches    |           |                            | Millimeters |             |           |
|--------------------|-----------|-----------|----------------------------|-------------|-------------|-----------|
|                    | A         | B         | C                          | A           | B           | C         |
| A                  | .420/.400 | .432/.415 | .330/.310                  | 10.67/10.16 | 11.05/10.54 | 8.38/7.87 |
| B, C, D & P        | .420/.400 | .460/.440 | .330/.310                  | 10.67/10.16 | 11.68/11.18 | 8.38/7.87 |
| E                  | .420/.400 | .480/.460 | .330/.310                  | 10.67/10.16 | 12.19/11.68 | 8.38/7.87 |
| F                  | .785/.745 | .275/.255 | .228/.208                  | 19.94/18.92 | 6.98/6.48   | 5.79/5.28 |
| G                  | .490/.470 | .275/.255 | .156/.136                  | 12.45/11.94 | 6.98/6.48   | 3.96/3.45 |
| H & R              | .581/.561 | .345/.325 | .156/.136                  | 14.76/14.25 | 8.76/8.26   | 3.96/3.45 |
| J                  | .326/.306 | .250/.230 | .088/.068                  | 8.28/7.77   | 6.35/5.84   | 2.24/1.73 |
| K                  | .410/.390 | .290/.270 | .088/.068                  | 10.41/9.91  | 7.37/6.86   | 2.24/1.73 |
| L                  | .385/.365 | .244/.224 | .074/.064                  | 9.78/9.27   | 6.20/5.69   | 1.88/1.63 |
| S                  | .678/.658 | .275/.255 | .156/.136                  | 17.22/16.71 | 6.98/6.48   | 3.96/3.45 |
| U                  | .940/.920 | .760/.740 | .080/.060                  | 23.88/23.37 | 19.30/18.80 | 2.03/1.52 |
| V                  | .550/.540 | .415/.405 | .250/.240                  | 13.97/13.72 | 10.54/10.29 | 6.35/6.10 |
| T                  | .598/.578 | .300/.280 | .228/.208                  | 15.19/14.68 | 7.62/7.11   | 5.79/5.28 |
| AA, AC             |           |           | See page 60 for dimensions |             |             |           |
| AB, AD, AE, AF, AG |           |           | See page 60 for dimensions |             |             |           |





Modifications Codes

DPXA Modifications Codes

- 4. Mounting holes .120 (3.05) dia. c'sink 100° to .225 (5.72) dia.
- 5. 4-40 clinch nuts.
- 6. Removable insert retainer plate.
- 7. Mounting holes .120 (3.05) dia. c'sink 82° to .230 (5.84) dia.
- 12. Mounting holes .132 (3.35)/.125 (3.18).
- 16. A106 insert with separator.
- 17. With grommet and mounting holes .120 (3.05) dia. countersunk 100° to .225 (5.72) dia.
- 70. Standard mounting with (LIF) contacts.
- 77. Same as -7 except with low insertion force (LIF) contacts (for LIF contact data).









DPXB and DPX2/3/4 Modification Codes

Some of the modification numbers used in the DPX lines apply to all types and some are applicable for only certain types. The following chart gives the modification number, the description, and the shell type in which they may be used (-33 is for plug shells, -34 is for receptacle shells).

|                                                                                     | Modification | Applicable Series                                                                                                        | Definition                                                                                            |
|-------------------------------------------------------------------------------------|--------------|--------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------|
| DESCRIBES STANDARD CONNECTOR HOUSING                                                | - 00**       | DPX2-33 and 34<br>DPX2-33A<br>DPX2-33F and 34F<br>DPX2-33M and 34M                                                       | Standard construction, mounting holes .120 (3.05) dia. and with tabs for junction shells.             |
|                                                                                     | - 00         | DPX2-34A                                                                                                                 | Standard construction - six floating eyelets and tabs for junction shells,                            |
|                                                                                     | - 00         | DPX2-33B<br>DPXB-33<br>DPX3-33<br>DPX4-33                                                                                | Standard construction, mounting holes .120 (3.05) dia. countersunk 82° to .230 (5.84) dia. - no tabs. |
|                                                                                     | - 00         | DPX2-34B<br>DPXB-34<br>DPX3-34<br>DPX4-34                                                                                | Standard construction, mounting holes 120 (3.05) dia. - no tabs.                                      |
| MODIFICATION 00                                                                     |              |                                                                                                                          |                                                                                                       |
|  | - 01         | DPX2-33 and 34<br>DPX2-33A<br>DPX2-34A<br>DPX2-33F and 34F<br>DPX2-33M-34M                                               | Standard construction and with standard junction shells.                                              |
|                                                                                     | - 01         | DPX2-34B/33B<br>DPXB-34                                                                                                  | With four #4-40 clinch nuts in mounting holes.                                                        |
|                                                                                     | - 01         | DPX3-34                                                                                                                  | With six #4-40 clinch nuts in mounting holes.                                                         |
|                                                                                     | - 01         | DPX4-34                                                                                                                  | With ten #440 clinch nuts in mounting holes.                                                          |
| MODIFICATION 01                                                                     |              |                                                                                                                          |                                                                                                       |
|  | - 02         | DPX2-33 and 34<br>DPX2-33A<br>DPX2-34A<br>DPX2-33F and 34F<br>DPX2-33M and 34M                                           | Standard construction and with 90° junction shells.                                                   |
|                                                                                     | - 02         | DPX2-33B and 34B<br>DPXB-33 and 34<br>DPX3-33 and 34<br>DPX4-33 and 34                                                   | Standard construction and with tabs for attaching junction shells.                                    |
|                                                                                     | - 02         | DPXBME-33 and 34<br>DPX2ME-33 and 34<br>DPX3ME-33 and 34<br>DPX4ME-33 and 34                                             | Standard construction and with tabs for attaching junction shells.                                    |
|                                                                                     |              |                                                                                                                          |                                                                                                       |
| MODIFICATION 02<br>ATTACHING TABS                                                   |              |                                                                                                                          |                                                                                                       |
| MODIFICATION 03                                                                     |              |                                                                                                                          |                                                                                                       |
|                                                                                     | - 03         | DPX2-33 and 34<br>DPX2-33A<br>DPX2-33F and 34F<br>DPX2-33M and 34M<br>DPXB-33 and 34<br>DPX3-33 and 34<br>DPX4-33 and 34 | Mounting holes .120 (3.05) dia. countersunk 100° to .230(5.84) dia.                                   |

 Applicable for all MA, ME, NA & NE Series Connectors.  
 Applicable to NE Series also.





## Modifications Codes

|                                                                                                                                                                                                                                                                              | Modification | Applicable Series                                                | Definition                                                                                                   |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------|------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------|
|  <p>MOUNTING HOLES<br/>.120 (3.05) DIA.<br/>C'SUNK 100° TO<br/>.230 (5.84) DIA.</p> <p>#4-40 THREAD</p> <p>ATTACHING TABS<br/>(2 PER RETAINING<br/>PLATE)</p> <p><b>MODIFICATION 04</b></p> | - 04**       | DPX2-33B<br>DPXB-33<br>DPX3-33<br>DPX4-33                        | .120 (3.05) dia. mounting holes countersunk 100° to .230 (5.84) dia. and tabs for attaching junction shells. |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                             |
|                                                                                                                                                                                                                                                                              |              |                                                                  | <b>ALTERNATE STYLE</b>                                                                                       |
|  <p>MOUNTING HOLES<br/>.137 (3.48) DIA.<br/>C'SUNK 82° TO<br/>.230 (5.84) DIA.</p> <p><b>MODIFICATION 08</b></p>                                                                            | - 08         | DPX2-33 and 34<br>DPX2-33F and 34F                               | Mounting holes .137 (3.48) dia. countersunk 82° to .230 (5.84) dia.                                          |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                                                                                                              |
|  <p>MOUNTING<br/>SLOTS (4)<br/>.208 (5.28)</p> <p><b>MODIFICATION 12</b></p>                                                                                                                | - 12         | DPX2-34B<br>DPXB-34                                              | With mounting slots .208 (5.28) wide.                                                                        |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                                                                                                              |
|  <p>MOUNTING<br/>SLOTS (4)<br/>.237 (6.02)</p> <p><b>MODIFICATION 13</b></p>                                                                                                               | - 13         | DPX2-34B<br>DPXB-34                                              | With mounting slots .237 (6.02) wide.                                                                        |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                                                                                                              |
| <p>(SEE PAGE 62 FOR JUNCTION<br/>SHELL CONFIGURATIONS)</p> <p><b>MODIFICATION 14</b></p>                                                                                                                                                                                     | - 14         | DPX2-33B<br>DPXB-33<br>DPX2-34B<br>DPXB-34<br>DPX3-33<br>DPX3-34 | With straight junction shelf. (Not available on DPX4)                                                        |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                                                                                                              |
|  <p>#4-40 CLINCH NUTS</p> <p>#4-40 THREAD</p> <p>ATTACHING TABS<br/>(2 PER RETAINING<br/>PLATE)</p> <p><b>MODIFICATION 17</b></p>                                                          | - 17         | DPX2-33B<br>DPXB-33<br>DPX2-34B<br>DPXB-34                       | With four #4-40 clinch nuts in mounting holes and tabs for attaching junction shells.                        |
|                                                                                                                                                                                                                                                                              | - 17         | DPX3-34                                                          | With six #4-40 clinch nuts in mounting holes and tabs for attaching junction shells.                         |
|                                                                                                                                                                                                                                                                              | - 17         | DPX4-34                                                          | With ten #4-40 clinch nuts in mounting holes and tabs for attaching junction shells.                         |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                                                                                                              |
|                                                                                                                                                                                                                                                                              |              |                                                                  | <b>ALTERNATE STYLE</b>                                                                                       |
|  <p>#4-40 CLINCH NUTS</p> <p>#4-40 THREAD</p> <p>ATTACHING TABS<br/>(2 PER RETAINING<br/>PLATE)</p> <p><b>MODIFICATION 18</b></p>                                                         | - 18         | DPX2-33B<br>DPXB-33<br>DPX2-34B<br>DPXB-34<br>DPX3-34            | With six #4-40 clinch nuts in mounting holes and tabs for attaching junction shells.                         |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                                                                                                              |
|                                                                                                                                                                                                                                                                              |              |                                                                  |                           |
|                                                                                                                                                                                                                                                                              |              |                                                                  | <b>ALTERNATE STYLE</b>                                                                                       |

 Applicable for all MA, ME, NA & NE Series Connectors.

Dimensions shown in inches (mm)  
Specifications and dimensions subject to change

## Modifications Codes



|                                                                                                                                                                                                                                                                                      | Modification | Applicable Series                                                                                                                                   | Definition                                                                                                      |
|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------|
|  <p>#4-40 CLINCH NUTS</p> <p><b>MODIFICATION 19</b></p>                                                                                                                                             | - 19**       | DPX2-33B<br>DPXB-33<br>DPX2-34B<br>DPXB-34<br>DPX3-33<br>DPX3-34 (Same as Code -01)                                                                 | With six #4-40 clinch nuts in mounting holes.<br><br>Do not assign - use -01 code                               |
|                                                                                                                                                                                                                                                                                      | - 20         | DPX2-33A<br>DPX2-34A                                                                                                                                | Standard construction without tabs on insert retaining plate.                                                   |
|                                                                                                                                                                                                                                                                                      | - 22         | DPX2-33 and 34<br>DPX2-33A<br>DPX2-33B<br>DPXB-33<br>DPX2-33M and 34M<br>DPX3-33<br>DPXBME, DPX2ME, DPX3ME,<br>DPX4ME - 33 only<br>DPX2-33F and 34F | With eight #4-40 clinch nuts in mounting holes.<br><br>Same as 01. 01 Recommended                               |
| <p>SUPERSEDED BY<br/>01 MOD.</p> <p><b>MODIFICATION 22</b></p>                                                                                                                                                                                                                       |              |                                                                                                                                                     |                                                                                                                 |
|  <p>.022 (0.56) MAX.<br/>.014 (0.36) MAX.<br/>4 PLACES<br/>.255 (6.48) DIA. MAX.<br/>RIVET<br/>4 REQD.<br/>FRONT FACE OF<br/>FLANGE<br/>- 33 PLUG<br/>- 34 RECEPT.</p> <p><b>MODIFICATION 23</b></p> | - 23         | DPX2-33 and 34<br>DPX2-33A<br>DPX2-33B<br>DPXB-33<br>DPX2-34B<br>DPXB-34<br>DPX3-33 and 34<br>DPX4-33 and 34<br>DPX2-33F and 34F                    | With floating eyelets.                                                                                          |
|                                                                                                                                                                                                                                                                                      | - 24         | DPX2-34A<br>DPX2-33B                                                                                                                                | With six mounting holes .208 (5.28) dia. (Floating eyelets omitted)                                             |
|  <p>MOUNTING<br/>HOLES(4), .156(3.96)<br/>DIA.</p> <p><b>MODIFICATION 25</b></p>                                                                                                                   | - 25         | DPX2-34B<br>DPXB-34                                                                                                                                 | With four mounting holes .157 (3.99)/.155 (3.94) dia. (Clinch nuts omitted)                                     |
|                                                                                                                                                                                                                                                                                      | - 26         | DPX2-34B<br>DPXB-34<br>DPX3-34                                                                                                                      | Mounting holes .120 (3.05) dia. countersunk 82° to .230 (5.84) dia. and has tabs for attaching junction shells. |
|  <p>MOUNTING<br/>HOLES(4), .120 (3.05)<br/>DIA., C'SUNK 82° TO<br/>.230 (5.84) DIA.</p> <p><b>MODIFICATION 26</b></p>                                                                             | - 29         | DPX2-34A                                                                                                                                            | With interfacial seal (if pins) without junction shell tabs and military gold plating on the contact.           |
|                                                                                                                                                                                                                                                                                      | - 29         | DPXBME-34P & 33S<br>DPX2ME-34P & 33S<br>DPX3ME-34P & 33S<br>DPX4ME-34P & 33S                                                                        | Standard except less grommet*<br><br>* On the A106S layout the grommet is replaced by the separator.            |
|                                                                                                                                                                                                                                                                                      | - 30         | DPXBME-34P<br>DPX2ME-34P<br>DPX3ME-34P<br>DPX4ME-34P                                                                                                | Standard except less grommet and with tabs for attaching junction shells. (-34 pin only)                        |
|                                                                                                                                                                                                                                                                                      | - 31         | DPXBME-34P<br>DPX2ME-34P<br>DPX3ME-34P<br>DPX4ME-34P                                                                                                | Standard except less grommet and with floating bushings. (Slatted shells).                                      |
|                                                                                                                                                                                                                                                                                      | - 33         | DPXBME-34P<br>DPX2ME-34P<br>DPX3ME-34P<br>DPX4ME-34P                                                                                                | Standard except less grommet and with clinch nuts in mounting holes.                                            |
|                                                                                                                                                                                                                                                                                      | - 37         | DPXBME-34P<br>DPX2ME-34P<br>DPX3ME-34P<br>DPX4ME-34P                                                                                                | Standard less grommet and with clinch nuts in mounting holes and with tabs for attaching junction shells.       |

△ Applicable for all MA, ME, NA and NE Series Connectors.



\*\*Indicates polarizing position. (See page 72)

## Modifications Codes

| Modification                                                                                                                                                                                                                                             | Applicable Series                                                                                         | Definition                                                                                                                                                     |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------|
|  <p><b>MODIFICATION 39</b></p>                                                                                                                                          | <p>- 39**</p> <p>DPXB-33 &amp; 34<br/>DPX2-33B<br/>DPX2-34B<br/>DPX3-33 &amp; 34<br/>DPX4-33 &amp; 34</p> | <p>With floating eylets &amp; tabs for attaching junction shells.</p> <p></p> |
|  <p><b>ALTERNATE STYLE</b></p>                                                                                                                                          |                                                                                                           |                                                                                                                                                                |
| <p>The -7*** and 8*** Modification Codes are reserved for connectors which have Low Insertion Force (LIF) Contacts. The LIF design is not applicable to thermocouple contacts, coaxial contacts and contacts larger than size 8 and Standard size 20</p> |                                                                                                           |                                                                                                                                                                |
| - 70**                                                                                                                                                                                                                                                   | All DPX series with LITTLE CAESAR retention                                                               | Same as -00 with addition of LIF contacts<br>See Contact Section Page 54                                                                                       |
| - 71                                                                                                                                                                                                                                                     | All DPX series with LITTLE CAESAR retention                                                               | Same as -31 with addition of LIF contacts<br>See Contact Section Page 54                                                                                       |
| - 72                                                                                                                                                                                                                                                     | All DPX series with LITTLE CAESAR retention                                                               | Same as -01 with addition of LIF contacts<br>See Contact Section Page 54                                                                                       |
| - 73                                                                                                                                                                                                                                                     | All DPX series with LITTLE CAESAR retention                                                               | Same as -23 with addition of LIF contacts<br>See Contact Section Page 54                                                                                       |
| - 74                                                                                                                                                                                                                                                     | All DPX series with LITTLE CAESAR retention                                                               | Same as -33 with addition of LIF contacts<br>See Contact Section Page 54                                                                                       |
| - 75                                                                                                                                                                                                                                                     | All DPX series with LITTLE CAESAR retention                                                               | Same as -02 with addition of LIF contacts<br>See Contact Section Page 54                                                                                       |
| - 76                                                                                                                                                                                                                                                     | All DPX as listed for code -22                                                                            | Same as -22 with addition of LIF contacts                                                                                                                      |
| - 77                                                                                                                                                                                                                                                     | All DPXB series                                                                                           | Mounting holes .120 (3.05) dia. countersunk 82° to .230 (5.84) dia. and has LIF contacts.                                                                      |
| - 78                                                                                                                                                                                                                                                     |                                                                                                           |                                                                                                                                                                |
| - 79                                                                                                                                                                                                                                                     | All DPX series with LITTLE CAESAR retention                                                               | Same as -29 with addition of LIF contacts                                                                                                                      |



 Applicable for all MA, ME, NA and NE Series Connectors.

 Applicable for NE Series Also.

\*\*Indicates polarizing position. (See page 72)







## Polarization

### Two Post Type



### Face View of Engaging End


### Three Post Type



Dimensions shown in inches (mm)  
Specifications and dimensions subject to change

Polarization

Positions



Dark areas represent post

Two Post Type

| DPX2 33 PLUG MALE SHELL ONLY |           |            |          |           |            | DPX2 34 RECEPTACLE FEMALE SHELL ONLY |           |            |          |           |            |
|------------------------------|-----------|------------|----------|-----------|------------|--------------------------------------|-----------|------------|----------|-----------|------------|
| Position                     | Left Post | Right Post | Position | Left Post | Right Post | Position                             | Left Post | Right Post | Position | Left Post | Right Post |
| 01                           | 4         | 4          | 09       | 3         | 3          | 01                                   | 1         | 1          | 09       | 2         | 2          |
| 02                           | 5         | 4          | 10       | 4         | 2          | 02                                   | 1         | 6          | 10       | 3         | 1          |
| 03                           | 6         | 4          | 11       | 2         | 2          | 03                                   | 1         | 5          | 11       | 3         | 3          |
| 04                           | 2         | 4          | 12       | 3         | 2          | 04                                   | 1         | 3          | 12       | 3         | 2          |
| 05                           | 3         | 4          | 13       | 2         | 1          | 05                                   | 1         | 2          | 13       | 4         | 3          |
| 06                           | 4         | 3          | 14       | 3         | 1          | 06                                   | 2         | 1          | 14       | 4         | 2          |
| 07                           | 5         | 3          | 15       | 2         | 6          | 07                                   | 2         | 6          | 15       | 5         | 3          |
| 08                           | 2         | 3          |          |           |            | 08                                   | 2         | 3          |          |           |            |


Three Post Type DPXB, DPX2 33B, DPX2 34B, DPX3 and DPX4

| PLUG SHELL |           |             |            |          |           |             |            | RECEPTACLE SHELL |           |             |            |          |           |             |            |
|------------|-----------|-------------|------------|----------|-----------|-------------|------------|------------------|-----------|-------------|------------|----------|-----------|-------------|------------|
| Position   | Left Post | Center Post | Right Post | Position | Left Post | Center Post | Right Post | Position         | Left Post | Center Post | Right Post | Position | Left Post | Center Post | Right Post |
| 01         | 1         | 1           | 1          | 51       | 3         | 2           | 5          | 01               | 4         | 4           | 4          | 51       | 6         | 3           | 2          |
| 02         | 2         | 1           | 1          | 52       | 4         | 2           | 5          | 02               | 4         | 4           | 3          | 52       | 6         | 3           | 1          |
| 03         | 3         | 1           | 1          | 53       | 5         | 2           | 5          | 03               | 4         | 4           | 2          | 53       | 6         | 3           | 6          |
| 04         | 4         | 1           | 1          | 54       | 6         | 2           | 5          | 04               | 4         | 4           | 1          | 54       | 6         | 3           | 5          |
| 05         | 5         | 1           | 1          | 55       | 1         | 2           | 4          | 05               | 4         | 4           | 6          | 55       | 1         | 3           | 4          |
| 06         | 6         | 1           | 1          | 56       | 2         | 2           | 4          | 06               | 4         | 4           | 5          | 56       | 1         | 3           | 3          |
| 07         | 1         | 1           | 6          | 57       | 3         | 2           | 4          | 07               | 5         | 4           | 4          | 57       | 1         | 3           | 2          |
| 08         | 2         | 1           | 6          | 58       | 4         | 2           | 4          | 08               | 5         | 4           | 3          | 58       | 1         | 3           | 1          |
| 09         | 3         | 1           | 6          | 59       | 5         | 2           | 4          | 09               | 5         | 4           | 2          | 59       | 1         | 3           | 6          |
| 10         | 4         | 1           | 6          | 60       | 6         | 2           | 4          | 10               | 5         | 4           | 1          | 60       | 1         | 3           | 5          |
| 11         | 5         | 1           | 6          | 61       | 1         | 2           | 3          | 11               | 5         | 4           | 6          | 61       | 2         | 3           | 4          |
| 12         | 6         | 1           | 6          | 62       | 2         | 2           | 3          | 12               | 5         | 4           | 5          | 62       | 2         | 3           | 3          |
| 13         | 1         | 1           | 5          | 63       | 3         | 2           | 3          | 13               | 6         | 4           | 4          | 63       | 2         | 3           | 2          |
| 14         | 2         | 1           | 5          | 64       | 4         | 2           | 3          | 14               | 6         | 4           | 3          | 64       | 2         | 3           | 1          |
| 15         | 3         | 1           | 5          | 65       | 5         | 2           | 3          | 15               | 6         | 4           | 2          | 65       | 2         | 3           | 6          |
| 16         | 4         | 1           | 5          | 66       | 6         | 2           | 3          | 16               | 6         | 4           | 1          | 66       | 2         | 3           | 5          |
| 17         | 5         | 1           | 5          | 67       | 1         | 2           | 2          | 17               | 6         | 4           | 6          | 67       | 3         | 3           | 4          |
| 18         | 6         | 1           | 5          | 68       | 2         | 2           | 2          | 18               | 6         | 4           | 5          | 68       | 3         | 3           | 3          |
| 19         | 1         | 1           | 4          | 69       | 3         | 2           | 2          | 19               | 1         | 4           | 4          | 69       | 3         | 3           | 2          |
| 20         | 2         | 1           | 4          | 70       | 4         | 2           | 2          | 20               | 1         | 4           | 3          | 70       | 3         | 3           | 1          |
| 21         | 3         | 1           | 4          | 71       | 5         | 2           | 2          | 21               | 1         | 4           | 2          | 71       | 3         | 3           | 6          |
| 22         | 4         | 1           | 4          | 72       | 6         | 2           | 2          | 22               | 1         | 4           | 1          | 72       | 3         | 3           | 5          |
| 23         | 5         | 1           | 4          | 73       | 1         | 3           | 1          | 23               | 1         | 4           | 6          | 73       | 4         | 2           | 4          |
| 24         | 6         | 1           | 4          | 74       | 2         | 3           | 1          | 24               | 1         | 4           | 5          | 74       | 4         | 2           | 3          |
| 25         | 1         | 1           | 3          | 75       | 3         | 3           | 1          | 25               | 2         | 4           | 4          | 75       | 4         | 2           | 2          |
| 26         | 2         | 1           | 3          | 76       | 4         | 3           | 1          | 26               | 2         | 4           | 3          | 76       | 4         | 2           | 1          |
| 27         | 3         | 1           | 3          | 77       | 5         | 3           | 1          | 27               | 2         | 4           | 2          | 77       | 4         | 2           | 6          |
| 28         | 4         | 1           | 3          | 78       | 6         | 3           | 1          | 28               | 2         | 4           | 1          | 78       | 4         | 2           | 5          |
| 29         | 5         | 1           | 3          | 79       | 1         | 3           | 6          | 29               | 2         | 4           | 6          | 79       | 5         | 2           | 4          |
| 30         | 6         | 1           | 3          | 80       | 2         | 3           | 6          | 30               | 2         | 4           | 5          | 80       | 5         | 2           | 3          |
| 31         | 1         | 1           | 2          | 81       | 3         | 3           | 6          | 31               | 3         | 4           | 4          | 81       | 5         | 2           | 2          |
| 32         | 2         | 1           | 2          | 82       | 4         | 3           | 6          | 32               | 3         | 4           | 3          | 82       | 5         | 2           | 1          |
| 33         | 3         | 1           | 2          | 83       | 5         | 3           | 6          | 33               | 3         | 4           | 2          | 83       | 5         | 2           | 6          |
| 34         | 4         | 1           | 2          | 84       | 6         | 3           | 6          | 34               | 3         | 4           | 1          | 84       | 5         | 2           | 5          |
| 35         | 5         | 1           | 2          | 85       | 1         | 3           | 5          | 35               | 3         | 4           | 6          | 85       | 6         | 2           | 4          |
| 36         | 6         | 1           | 2          | 86       | 2         | 3           | 5          | 36               | 3         | 4           | 5          | 86       | 6         | 2           | 3          |
| 37         | 1         | 2           | 1          | 87       | 3         | 3           | 5          | 37               | 4         | 3           | 4          | 87       | 6         | 2           | 2          |
| 38         | 2         | 2           | 1          | 88       | 4         | 3           | 5          | 38               | 4         | 3           | 3          | 88       | 6         | 2           | 1          |
| 39         | 3         | 2           | 1          | 89       | 5         | 3           | 5          | 39               | 4         | 3           | 2          | 89       | 6         | 2           | 6          |
| 40         | 4         | 2           | 1          | 90       | 6         | 3           | 5          | 40               | 4         | 3           | 1          | 90       | 6         | 2           | 5          |
| 41         | 5         | 2           | 1          | 91       | 1         | 3           | 4          | 41               | 4         | 3           | 6          | 91       | 1         | 2           | 4          |
| 42         | 6         | 2           | 1          | 92       | 2         | 3           | 4          | 42               | 4         | 3           | 5          | 92       | 1         | 2           | 3          |
| 43         | 1         | 2           | 6          | 93       | 3         | 3           | 4          | 43               | 5         | 3           | 4          | 93       | 1         | 2           | 2          |
| 44         | 2         | 2           | 6          | 94       | 4         | 3           | 4          | 44               | 5         | 3           | 3          | 94       | 1         | 2           | 1          |
| 45         | 3         | 2           | 6          | 95       | 5         | 3           | 4          | 45               | 5         | 3           | 2          | 95       | 1         | 2           | 6          |
| 46         | 4         | 2           | 6          | 96       | 6         | 3           | 4          | 46               | 5         | 3           | 1          | 96       | 1         | 2           | 5          |
| 47         | 5         | 2           | 6          | 97       | 1         | 3           | 3          | 47               | 5         | 3           | 6          | 97       | 2         | 2           | 4          |
| 48         | 6         | 2           | 6          | 98       | 2         | 3           | 3          | 48               | 5         | 3           | 5          | 98       | 2         | 2           | 3          |
| 49         | 1         | 2           | 5          | 99       | 3         | 3           | 3          | 49               | 6         | 3           | 4          | 99       | 2         | 2           | 2          |
| 50         | 2         | 2           | 5          |          |           |             |            | 50               | 6         | 3           | 3          |          |           |             |            |

The last two digits in the DPX nomenclature (ex: DPXB-8-33B-0014) refer to the polarizing post position. When the last two digits are omitted it means the polarizing posts will not be assembled and position number is not stamped on the connector. This allows the customer to position the posts themselves and then stamp the appropriate number on the shell. If the last two digits are made 00 it means the polarizing posts are deleted.


## Panel Cutouts

### DPXA




NOTE - WHEN USING THE -2301 FLOATING EYELET MODIFICATION, ADD .050 (1.27) TO THE CUTOUT SIZE TO ALLOW FOR FLOAT (EXCEPTION -34A)

### DPXB



- 33 Front Mount



- 33 Rear Mount  
- 34 Rear Mount  
- 34 Front Mount




H

Rack and Panel


## Panel Cutouts

DPX2


All tolerances are  $\pm .015$  (0.38) unless otherwise noted.




- 33 FRONT MOUNT




- 33 REAR MOUNT




- 34 FRONT  
OR REAR MOUNT



- 33A & - 33B FRONT MOUNT




- 33A REAR MOUNT




- 34B FRONT MOUNT

For - 23 float mtg. mod. 1.78 (45.21).



- 34A REAR MOUNT  
(-34A FRONT MOUNT CONSULT FACTORY)




- 33B REAR MOUNT  
- 33B REAR MOUNT


## Panel Cutouts

DPX3

All tolerances are  $\pm .015$  (0.38) unless otherwise noted.




DPX4



Sealing Plugs - DPX\*ME (for environmental requirements)


Material: Teflon  
(All others thermoplastic)



| Part Number  | Contact Size   | Color  | A          | B           | C                           |
|--------------|----------------|--------|------------|-------------|-----------------------------|
| 225-1013-000 | 22             | Black  | .063 (1.6) | .040 (1.0)  | .469 (11.9)                 |
| 225-0070-000 | 20             | Red    | .085 (2.2) | .053 (1.3)  | .805 / .755 (20.5 / 19.2)   |
| 225-0071-000 | 16             | Blue   | .115 (2.9) | .074 (1.88) | 1.472 / 1.422 (37.4 / 36.1) |
| 225-0072-000 | 12             | Yellow | .171 (4.3) | .120 (3.0)  | 1.441 / 1.391 (36.6 / 35.5) |
| 225-0090-000 | #5 and #9 Coax | White  | .365 (9.3) | .287 (7.3)  | .835 (21.2)                 |

Filler Plugs - DPX\*


Material: Teflon  
(All others thermoplastic)



| Part Number  | Contact Size            | Color  | A          | B          | C            |
|--------------|-------------------------|--------|------------|------------|--------------|
| 225-0094-000 | 22                      | Black  | .069 (1.7) | .051 (1.3) | .420 (10.7)  |
| 225-0095-000 | 20                      | Red    | .083 (2.1) | .069 (1.7) | .350 (8.9)   |
| 225-0096-000 | 16                      | Blue   | .131 (3.3) | .108 (2.7) | .320 (8.1)   |
| 225-0097-000 | 12                      | Yellow | .187 (4.7) | .156 (4.0) | .320 (8.1)   |
| 225-0098-000 | #5 Coax (Pin)           | White  | .275 (7.0) | .251 (6.4) | .450 (11.4)  |
| 225-0099-000 | #5 and #9 Coax (Socket) | White  | .275 (7.0) | .251 (6.4) | 1.061 (26.9) |


## Junction Shells

### 90° Angle




| Style        | Part Number |
|--------------|-------------|
| (Right) DPXA | 20745-22    |
| (Left) DPXA  | 20745-23    |
| (Right) DPX2 | 20745-10    |
| (Left) DPX2  | 20745-11    |

### 90° ANGLE DPX2 JUNCTION SHELL (SIDE OUTLET)



| Style | Part Number |
|-------|-------------|
| DPX2  | 20745-12    |


### STRAIGHT JUNCTION SHELL



| Style | Part Number |
|-------|-------------|
| DPXA  | 20745-21    |
| DPX2  | 20745-8     |


\* DPX2 Junction Shells are also used on DPXB connectors.

### (DPXA ONLY) DIECAST STRAIGHT JUNCTION SHELL




| Style | Part Number |
|-------|-------------|
| DPXA  | 22017       |

### (DPXA ONLY) DIECAST STRAIGHT JUNCTION SHELL



| Style | Part Number |
|-------|-------------|
| DPXA  | 22017-2     |

### (DPXA ONLY) DIECAST 90° ANGLE JUNCTION SHELL



| Style | Part Number |
|-------|-------------|
| DPXA  | 22017-1     |

Diecast junction shells may be used on DPXA connectors. They have 4-40 NC-2B tapped mounting holes for attaching to the shell mounting hardware.

## Dust Caps



34

Conductive (black)

DPXB-60-1 for 34 Shell  
Conductive Dust Caps  
025-0767-001  
Protect Against  
Static Electricity



33

Conductive (black)

DPXA-59-1 for 33 Shells  
025-0749-001

Coaxial Cable Reference Guide

For BKA\* DPX Series (Crimp, & Solder)  
Reference MIL-C-17D & DPX NE/NA MIL-C-81659 Series

| RG/U Type | Inner Conductor | Dielectric Material | DOD (Inch) | Jacket Material | O.D (Inch) | Weight (lbs/ft) | Max Oper. Temp, Range ( C ) | Max Oper. Voltage (Volts RMS) | Suggested Alt Cable | Code Crimp Type Coax | Code Solder Type Coax | DPX NE/NA Military | BKA* ARINC Type Coax       |
|-----------|-----------------|---------------------|------------|-----------------|------------|-----------------|-----------------------------|-------------------------------|---------------------|----------------------|-----------------------|--------------------|----------------------------|
| 7         | 0.0359 "        | Air-space PE        | 0.250      | PVC             | 0.370      | 0.080           | -40 + 80                    | 1,000                         | Use RG63B           | —                    | I                     | —                  | —                          |
| 9         | 0.0855"         | PE                  | 0.280      | PVC             | 0.420      | 0.140           | -40 + 80                    | 4,000                         | Use RG214           | —                    | R,AC                  | —                  | Size 1(71W1)               |
| 55        | 0.0320 "        | PE                  | 0.116      | PE              | 0.206 Max. | 0.032           | -55 + 80                    | 1,900                         | Use RG55B           | S                    | C, J                  | —                  | Size 1(71W1)               |
| 58        | 0.0320"BC       | PE                  | 0.116      | PVC             | 0.195      | 0.029           | -40 + 80                    | 1,900                         | Use RG58B           | D,P,G JAC,AD         | C, J, Z AB            | Size 5/9 Seal 1    | Size 1(71W1) Size 5        |
| 59        | 0.0253 "        | PE                  | 0.146      | PVC             | 0.242      | 0.032           | -40 + 80                    | 2,300                         | Use RG59B           | A,F,T                | D                     | —                  | —                          |
| 59B       | 0.0230"         | PE                  | 0.146      | PVC             | 0.242      | 0.032           | -40 + 80                    | 2,300                         | Use up to 1000 MHz  | —                    | —                     | —                  | —                          |
| 62        | 0.0253"         | Air-space PE        | 0.146      | PVC             | 0.242      | 0.038           | -40 + 80                    | 750                           | Use RG62A           | A,F,T                | E                     | —                  | —                          |
| 62A       | 0.0253"         | Air-space PE        | 0.146      | PVC             | 0.242      | 0.038           | -40 + 80                    | 750                           | —                   | —                    | —                     | —                  | —                          |
| 71        | 0.0253"         | Air-space PE        | 0.146      | PVC             | 0.250 Max. | 0.046           | -40 + 80                    | 750                           | Use RG71B           | —                    | E                     | —                  | —                          |
| 115       | 0.0840"         | PTFE                | 0.250      | FG Braid        | 0.375      | 0.148           | -55 + 250                   | 5,000                         | Use RG115A          | V                    | —                     | —                  | Size 1(71W1)               |
| 142       | 0.0359"         | PTFE                | 0.116      | FG Braid        | 0.206 Max. | 0.047           | -55 + 250                   | 1,900                         | Use RG142A          | S,AE                 | —                     | Size 5/9 Seal 1    | Size 1(71W1) Size 1(71W1A) |
| 142B      | 0.0390"         | PTFE                | 0.116      | FEP             | 0.195      | 0.050           | -55 + 200                   | 1,900                         | —                   | —                    | —                     | —                  | Size 1(71W1A) Size 5       |
| 174       | 0.0189"         | PE                  | 0.060      | PVC             | 0.100      | 0.008           | -40 + 80                    | 1,500                         | —                   | D,H,U, AF            | —                     | Size 5/9 Seal 2    | Size 5 Size 12             |
| 178       | 0.0120"         | PTFE                | 0.036      | KEL-F           | 0.079 Max. | 0.0054          | -40 + 150                   | 1,000                         | Use RG178B          | ER,K,AG, L,M,AF      | —                     | Size 5/9 Seal 1    | Size 5                     |
| 179       | 0.0120 "        | PTFE                | 0.057      | KEL-F           | 0.094 Max. | 0.010           | -55 + 150                   | 1,200                         | Use RG179B          | D,H,U, AF            | —                     | Size 5/9 Seal 2    | Size 5                     |
| 179B      | 0.0120"         | PTFE                | 0.063      | FEP             | 0.100      | 0.010           | -55 + 200                   | 1,200                         | —                   | —                    | —                     | —                  | Size 5                     |
| 180       | 0.0120"         | PTFE                | 0.103      | KEL-F           | 0.141 Max. | 0.019           | -40 + 150                   | 1,500                         | Use RG180B          | CAB                  | B                     | Size 5/9 Seal 1    | Size 5                     |
| 180B      | 0.0120"         | PTFE                | 0.102      | FEP             | 0.145 Max. | 0.019           | -55 + 200                   | 1,500                         | —                   | AB                   | —                     | —                  | Size 5                     |
| 187       | 0.0120"         | PTFE                | 0.060      | PTFE            | 0.110 Max. | 0.010           | -55 + 250                   | 1,200                         | Use RG179B          | D,H,U, AF            | A,K                   | —                  | Size 5                     |
| 188       | 0.0201"         | PTFE                | 0.060      | PTFE            | 0.110 Max. | 0.011           | -55 + 250                   | 1,200                         | Use RG316           | D,A,U AF             | A,K                   | —                  | —                          |
| 195       | 0.0120"         | PTFE                | 0.102      | PTFE            | 0.155 Max. | 0.020           | -55 + 250                   | 1,500                         | Use RG180B          | CAB                  | B                     | —                  | Size 5                     |
| 196       | 0.0120'         | PTFE                | 0.034      | PTFE            | 0.080 Max. | 0.006           | -55 + 250                   | 1,000                         | Use RG178B          | E,R,K, L,AA,AG       | AA                    | Size 5/9 Seal 1    | Size 5                     |
| 214       | 0.0888"         | PE                  | 0.285      | PVC             | 0.425      | 0.126           | -40 + 80                    | 5,000                         | —                   | —                    | R,AC                  | —                  | Size 1(71W1) Size 1(71W1A) |
| 223       | 0.035 "         | pE                  | 0.116      | PVC             | 0.216 Max. | 0.034           | -40 + 80                    | 1,900                         | —                   | —                    | C,J                   | —                  | —                          |
| 225       | 0.0936"         | PTFE                | 0.285      | FG Braid        | 0.430      | 0.180           | -55 + 250                   | 5,000                         | —                   | —                    | —                     | Size 5/9 Seal 2    | Size 1(71W1)               |
| 316       | 0.0201          | PTFE                | 0.060      | FEP             | 0.102      | 0.012           | -55 + 200                   | 1,200                         | Use RG188A          | —                    | —                     | Size 5/9 Seal 2    | —                          |
| 393       | 0.0936"         | PTFE                | 0.285      | FEP             | 0.390      | 0.165           | -55 + 200                   | 5,000                         | Use RG225           | —                    | —                     | —                  | Size 1(71W1A)              |
| 400       | 0.0385"         | PTFE                | 0.116      | FEP             | 0.195      | 0.050           | -55 + 200                   | 1,900                         | —                   | —                    | —                     | —                  | Size 1(71W1)               |
| 402       | 0.0360"         | PTFE                | 0.119      | None            | 0.141      | 0.032           | -55 + 200                   | 2,500                         | Use RG142B          | —                    | —                     | —                  | Size 1(71W1) Size 1(71W1A) |

NOTE: This table is shown for reference only. ITT Cannon recommends that the above information be used as a guideline and may be subject to variation between various cable manufacturers. For specific information concerning the actual physical characteristics of a specific cable, contact the manufacturer.

