

- single or dual supply voltage options
- SPCO or DPCO output relay
- ♦ 8 selectable time ranges (0,1sec-100hrs)
- LED indicators for power supply and relay status
- 22.5mm DIN rail mount housing or 11pin plug in housing




## Off delay

Starting contact S on B1 closed Starting contact S on B1 open

Supply voltage(U) on Supply voltage(U) off

Output relay contact closed Output relay contact open



On the application of the supply voltage the time relay energises ready for the timing cycle. When the starting contact  ${\bf S}$  is closed the output relay pulls in immediately. Time delay  ${\bf f}$  starts when the starting contact is opened and the output relay drops out at the end of the time delay. If the supply voltage is removed before, or during time  ${\bf f}$ , the output relay will drop out immediately and the time relay will reset ready for the next timing cycle.












	supply voltage	ı T	TR7x -15+10%; rest -20+10%					
	frequency ran	uency range			48 - 63 Hz			
	max. delay tin	delay time						
	repeat accura	<	< 1% of the selected range					
	output spec.	-1)						
	relay type			l	2			
	I <sub>e</sub> AC-15	230V~	1,	5A	1,5A			
	I <sub>e</sub> AC-15	115V~	1,	5A	1,5A			
	I <sub>e</sub> DC-13	24V=	1,	5A	1,5A			
	I <sub>the</sub> @+20°C,	detached		8A	10A			
	I <sub>the</sub> @+60°C,	attached		5A	5A			
	expected life							
	mechanical op	1>	(10 <sup>7</sup>	1x10 <sup>7</sup>				
	electrical oper	ations	8>	(10⁴	1x10 <sup>5</sup>			
	screws	рс	pozidriv 1, slot 4mm					
	screw tightening torque			0,4Nm				
	operating con	perating conditions			-20 bis +60°C non condensing			

## Time ranges

		-					
	=			_=	-	=	
0,1s-	1s-	0,1min-	1min-	0,1h-	1h-	3h-	10h-
1,0s	10s	1min	10min	1h	10h	30h	100h

The time ranges are selected using the DIP switch settings illustrated left, and the required delay time is set using the potentiometer on the front plate.







## ordering information

part no	suppl	y	output	relay type	<i>71</i> .	housing type
TR01+	230V~/24V~=	6VA / 1W	DPCO	1	yes	В
TR04+	115V~/24V~=	6VA / 1W	DPCO	1	yes	В
TR08+	12V~=	0,7W	SPCO	2	yes	А
TR12+	230V~	6VA	SPCO	2	yes	А
TR13+	24V~=	1W	SPCO	2	yes	А
TR15+	115V~	6VA	SPCO	2	yes	А
TR41	230V~ / 24V~=	6VA / 1W	DPCO	1	no	G
TR42	230V~ / 24V~=	6VA / 1W	SPCO	1	no	G
TR71	230V $\sim$ w. transf.	2VA	DPCO	1	no	G
TR72	230V∼ w. transf.	2VA	SPCO	1	no	G

other voltages on request

