

DESIGN KIT

WE-HCI SMD Flat Wire High Current Inductors



7030

744 310 013

L:	0.13 μ H
I _R :	22 A
I _{sat} :	48 A
R _{DC} :	0.91 m Ω

744 310 150

L:	1.5 μ H
I _R :	7.5 A
I _{sat} :	12 A
R _{DC} :	12.7 m Ω

744 310 024

L:	0.24 μ H
I _R :	18 A
I _{sat} :	40 A
R _{DC} :	1.8 m Ω

744 310 200

L:	2.0 μ H
I _R :	6.5 A
I _{sat} :	9.0 A
R _{DC} :	14.2 m Ω

744 310 055

L:	0.52 μ H
I _R :	14 A
I _{sat} :	20 A
R _{DC} :	3.7 m Ω

744 310 095

L:	0.95 μ H
I _R :	11 A
I _{sat} :	13 A
R _{DC} :	6.2 m Ω

744 310 115

L:	1.15 μ H
I _R :	8.5 A
I _{sat} :	13 A
R _{DC} :	8.6 m Ω

7040

744 311 022

L:	0.22 μ H
I _R :	21 A
I _{sat} :	32 A
R _{DC} :	1.1 m Ω

744 311 220

L:	2.2 μ H
I _R :	9.0 A
I _{sat} :	13 A
R _{DC} :	11.4 m Ω

744 311 047

L:	0.4 μ H
I _R :	19 A
I _{sat} :	25 A
R _{DC} :	1.85 m Ω

744 311 330

L:	3.3 μ H
I _R :	6.5 A
I _{sat} :	11 A
R _{DC} :	17.2 m Ω

744 311 068

L:	0.68 μ H
I _R :	17 A
I _{sat} :	20 A
R _{DC} :	3.1 m Ω

744 311 470

L:	4.7 μ H
I _R :	6.0 A
I _{sat} :	7.0 A
R _{DC} :	19.5 m Ω

744 311 100

L:	1.0 μ H
I _R :	15 A
I _{sat} :	19 A
R _{DC} :	4.6 m Ω

744 311 150

L:	1.5 μ H
I _R :	11 A
I _{sat} :	14 A
R _{DC} :	6.6 m Ω

7050

744 314 024

L:	0.24 μ H
I _R :	20 A
I _{sat} :	28 A
R _{DC} :	1.0 m Ω

744 314 200

L:	2.0 μ H
I _R :	11.5 A
I _{sat} :	9.0 A
R _{DC} :	5.85 m Ω

744 314 850

L:	8.5 μ H
I _R :	4.0 A
I _{sat} :	4.5 A
R _{DC} :	30.4 m Ω

744 314 047

L:	0.47 μ H
I _R :	18 A
I _{sat} :	20 A
R _{DC} :	1.35 m Ω

744 314 330

L:	3.3 μ H
I _R :	9.0 A
I _{sat} :	8.0 A
R _{DC} :	9.0 m Ω

744 314 101

L:	10 μ H
I _R :	3.5 A
I _{sat} :	4.0 A
R _{DC} :	33 m Ω

744 314 076

L:	0.76 μ H
I _R :	15.5 A
I _{sat} :	15 A
R _{DC} :	2.25 m Ω

744 314 490

L:	4.9 μ H
I _R :	6.5 A
I _{sat} :	6.5 A
R _{DC} :	14.5 m Ω

744 314 110

L:	1.1 μ H
I _R :	15 A
I _{sat} :	13 A
R _{DC} :	3.15 m Ω

744 314 650

L:	6.5 μ H
I _R :	6.0 A
I _{sat} :	6.0 A
R _{DC} :	21.5 m Ω

744 314 150

L:	1.5 μ H
I _R :	13 A
I _{sat} :	11 A
R _{DC} :	4.3 m Ω

744 314 760

L:	7.6 μ H
I _R :	4.2 A
I _{sat} :	4.8 A
R _{DC} :	28.5 m Ω

EMC COMPONENTS | INDUCTORS | TRANSFORMERS | RF COMPONENTS | CIRCUIT PROTECTION | EMC SHIELDING MATERIAL | CONNECTORS | SWITCHES | ASSEMBLY TECHNIQUE | POWER ELEMENTS

Important information: Würth Elektronik's design kits contain reference components. These components correspond with the current product development status on the day of supply. Exchange of the reference components to components with up-to-date product development status is not carried out automatically. No liability is taken for the use of these reference components. Therefore, please request new samples prior to releases for series production and product release.

Please check datasheets on www.we-online.com for specifications. Würth Elektronik eiSos GmbH & Co. KG, EMC & Inductive Solutions. © 2011

www.we-online.com

All products
in stock!