




50/60 Hz Current Sensors – CS60 Series




The CS60 series is designed to measure current from 5 to 100 Arms. Applications include sensing branch circuit overload and detecting load drop or shutdown. The sensor functions as the encapsulated secondary of a current transformer, while the conductor carrying the current to be measured serves as the “one turn primary.” Sensitivity may be enhanced by increasing primary turns.


These parts are mountable on printed circuits and have a third terminal added for mechanical stability.

Samples of these and other current sensors are available for evaluation. To request samples, contact Coilcraft or visit www.coilcraft.com.

Typical Response



Typical Circuit



Part number	Sensed current (I_{rms})	V_{out} tolerance
CS60-050L	5-50 Arms	$\pm 10\%$
CS60-075L	5-75 Arms	$\pm 10\%$
CS60-100L	5-100 Arms	$\pm 10\%$

(For sensed current below 10 Arms, see CS60-010 data sheet)

- Ambient temperature range -40°C to $+85^{\circ}\text{C}$.
- Electrical specifications at 25°C .

Weight 13.8 – 15.4 g

Terminations Tin-silver over copper

Packaging 30 per tray

