# ENFORCER Security

## **Strobe Lights**

**SL-126Q** 6 to 12 Volt Use

SL-126-A24 6 to 24 Volt Use

**SL-126LQ Lens Only** 

#### Features:

- ► Easy 2-wire installation, regardless of voltage.
- ▶ If the strobe light is being powered by a backup battery, as the battery is drained, the strobe light will continue to function.
- Perfect for "informative" household burglar alarm use.
- Incorrect polarity cannot damage circuit or draw current.
- ► Low current consumption with long operating lifespan of over 300 continuous hours (2,000,000 flashes).
- ▶ Lens is made of high-impact resistant acrylic, in case of high impact resistant ABS plastic.
- ▶ Choice of amber, blue, clear, green, or red lens.





Clear









Green

Red

6 to 12 Volt Use 6 to 24 Volt Use **SL-126-A24Q/A - Amber** SL-126Q/A - Amber SL-126-A24Q/C - Clear SL-126Q/C - Clear SL-126Q/B - Blue SL-126-A24Q/B - Blue SL-126Q/G – Green SL-126-A24Q/G - Green **SL-126Q/R - Red** SL-126-A24Q/R - Red

#### Lens Only

SL-126LQ/A - Amber

SL-126LQ/C - Clear

SL-126LQ/B - Blue

SL-126LQ/G - Green

SL-126LQ/R - Red



(SL-126Q)

The SECO-LARM strobe light comes with a protective inner cover. This protects the high-voltage zenon tube when the colored lens has been removed



### **Specifications:**

Model #	SL-126	SL-126-A24
Operating voltage	6-12VDC	6-24VDC
Current draw	200mA±20%@12VDC	150mA±20%@24VDC
Flash rate	Over 90/min@12VDC	Over 100/min@24VDC
Candle power	100,000	
Input connections	Red/Positive, Black/Ground	
Leads	#18 Gauge UL Listed	N/A
Electrical Protection	Reverse polarity protected	
Operating life	2,000,000 flashes (300 hours continuous)	
Environment	-22°~140° F (-30°~60° C)	
Base	High-impact black ABS	
Lens	High-impact resistant acrylic	
Dimensions	2 <sup>26</sup> / <sub>32</sub> " x 3 <sup>15</sup> / <sub>16</sub> " (74 x 100 mm)	

Copyright © 2009 SECO-LARM U.S A., Inc. All rights Reserved.

The SECO-LARM policy is one of continual development. For that reason SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints



Email: info@seco-larm.com Fax: 1-949-261-7326



