

DESIGN KIT

WE-LQSH SMD Semi-Shielded High Saturation Power Inductor



2010

744 050 200 047	744 050 200 10	744 050 200 15	744 050 200 22	744 050 200 47	744 050 201 00
L: 0.47 μ H	L: 1 μ H	L: 1.5 μ H	L: 2.2 μ H	L: 4.7 μ H	L: 10 μ H
R _{DC} : 41 m Ω	R _{DC} : 75 m Ω	R _{DC} : 110 m Ω	R _{DC} : 142 m Ω	R _{DC} : 370 m Ω	R _{DC} : 680 m Ω
I _{sat} : 4.7 A	I _{sat} : 3.85 A	I _{sat} : 2.3 A	I _{sat} : 2.15 A	I _{sat} : 1.5 A	I _{sat} : 0.95 A
I _b : 2.2 A	I _b : 1.65 A	I _b : 1.4 A	I _b : 1.25 A	I _b : 0.8 A	I _b : 0.58 A

2512

744 050 240 047	744 050 240 10	744 050 240 15	744 050 240 22	744 050 240 47	744 050 241 00
L: 0.47 μ H	L: 1 μ H	L: 1.5 μ H	L: 2.2 μ H	L: 4.7 μ H	L: 10 μ H
R _{DC} : 29 m Ω	R _{DC} : 48 m Ω	R _{DC} : 60 m Ω	R _{DC} : 100 m Ω	R _{DC} : 225 m Ω	R _{DC} : 435 m Ω
I _{sat} : 5.6 A	I _{sat} : 4.2 A	I _{sat} : 3.5 A	I _{sat} : 3 A	I _{sat} : 1.9 A	I _{sat} : 1.2 A
I _b : 2.9 A	I _b : 2.35 A	I _b : 2.1 A	I _b : 1.6 A	I _b : 1 A	I _b : 0.8 A

3012

744 050 310 047	744 050 310 10	744 050 310 15	744 050 310 22	744 050 310 47	744 050 311 00
L: 0.47 μ H	L: 1 μ H	L: 1.5 μ H	L: 2.2 μ H	L: 4.7 μ H	L: 10 μ H
R _{DC} : 28 m Ω	R _{DC} : 45 m Ω	R _{DC} : 64 m Ω	R _{DC} : 90 m Ω	R _{DC} : 196 m Ω	R _{DC} : 395 m Ω
I _{sat} : 8 A	I _{sat} : 5.4 A	I _{sat} : 4.1 A	I _{sat} : 3.35 A	I _{sat} : 2.5 A	I _{sat} : 1.45 A
I _b : 3.15 A	I _b : 2.4 A	I _b : 2.2 A	I _b : 1.75 A	I _b : 1.2 A	I _b : 0.85 A

4020

744 050 420 047	744 050 420 10	744 050 420 15	744 050 420 22	744 050 420 33	744 050 420 47
L: 0.47 μ H	L: 1 μ H	L: 1.5 μ H	L: 2.2 μ H	L: 3.3 μ H	L: 4.7 μ H
R _{DC} : 18 m Ω	R _{DC} : 22 m Ω	R _{DC} : 30 m Ω	R _{DC} : 40 m Ω	R _{DC} : 60 m Ω	R _{DC} : 90 m Ω
I _{sat} : 15.5 A	I _{sat} : 9.5 A	I _{sat} : 8.7 A	I _{sat} : 7.6 A	I _{sat} : 5.9 A	I _{sat} : 4.9 A
I _b : 4.5 A	I _b : 4 A	I _b : 3.2 A	I _b : 2.6 A	I _b : 2.3 A	I _b : 2.1 A

4020

744 050 420 68	744 050 421 00
L: 6.8 μ H	L: 10 μ H
R _{DC} : 130 m Ω	R _{DC} : 180 m Ω
I _{sat} : 4.2 A	I _{sat} : 3.5 A
I _b : 1.9 A	I _b : 1.7 A

Important information: Würth Elektronik's design kits contain reference components. These components correspond with the current product development status on the day of supply. Exchange of the reference components to components with up-to-date product development status is not carried out automatically. No liability is taken for the use of these reference components. Therefore, please request new samples prior to releases for series production and product release.

Please check datasheets on www.we-online.com for specifications. Würth Elektronik eiSos GmbH & Co. KG, EMC & Inductive Solutions. © 2016