



SIRIUS soft starter 200-600 V 32 A, 110-250 V AC Screw terminals Thermistor input

|   |   |
|---|---|
| <b>product brand name</b>   | SIRIUS  |
| <b>product category</b>   | Hybrid switching devices  |
| <b>product designation</b>  | Soft starter  |
| <b>product type designation</b>   | 3RW52   |
| <b>manufacturer's article number</b>  |   |
| <ul style="list-style-type: none"> <li>• of standard HMI module usable</li> <li>• of high feature HMI module usable</li> <li>• of communication module PROFINET standard usable</li> <li>• of communication module PROFIBUS usable</li> <li>• of communication module Modbus TCP usable</li> <li>• of communication module Modbus RTU usable</li> <li>• of communication module Ethernet/IP</li> <li>• of circuit breaker usable at 400 V</li> <li>• of circuit breaker usable at 500 V</li> <li>• of circuit breaker usable at 400 V at inside-delta circuit</li> <li>• of circuit breaker usable at 500 V at inside-delta circuit</li> <li>• of the gG fuse usable up to 690 V</li> <li>• of the gG fuse usable at inside-delta circuit up to 500 V</li> <li>• of full range R fuse link for semiconductor protection usable up to 690 V</li> <li>• of back-up R fuse link for semiconductor protection usable up to 690 V</li> </ul> | <ul style="list-style-type: none"> <li><a href="#">3RW5980-0HS00</a></li> <li><a href="#">3RW5980-0HF00</a></li> <li><a href="#">3RW5980-0CS00</a></li> <li><a href="#">3RW5980-0CP00</a></li> <li><a href="#">3RW5980-0CT00</a></li> <li><a href="#">3RW5980-0CR00</a></li> <li><a href="#">3RW5980-0CE00</a></li> <li><a href="#">3RV2032-4VA10; Type of coordination 1, Iq = 65 kA, CLASS 10</a></li> <li><a href="#">3RV2032-4VA10; Type of coordination 1, Iq = 10 kA, CLASS 10</a></li> <li><a href="#">3RV2032-4JA10; Type of coordination 1, Iq = 65 kA, CLASS 10</a></li> <li><a href="#">3RV2032-4JA10; Type of coordination 1, Iq = 10 kA, CLASS 10</a></li> <li><a href="#">3NA3824-6; Type of coordination 1, Iq = 65 kA</a></li> <li><a href="#">3NA3824-6; Type of coordination 1, Iq = 65 kA</a></li> <li><a href="#">3NE1818-0; Type of coordination 2, Iq = 65 kA</a></li> <li><a href="#">3NE8022-1; Type of coordination 2, Iq = 65 kA</a></li> </ul> |
| <b>General technical data</b>   |   |
| <b>starting voltage [%]</b>   | 30 ... 100 %  |
| <b>stopping voltage [%]</b>   | 50 %; non-adjustable  |
| <b>start-up ramp time of soft starter</b>   | 0 ... 20 s  |
| <b>current limiting value [%] adjustable</b>  | 130 ... 700 %   |
| <b>certificate of suitability</b>   |   |
| <ul style="list-style-type: none"> <li>• CE marking</li> <li>• UL approval</li> <li>• CSA approval</li> </ul>   | <ul style="list-style-type: none"> <li>Yes</li> <li>Yes</li> <li>Yes</li> </ul>   |
| <b>product component</b>  |   |
| <ul style="list-style-type: none"> <li>• HMI-High Feature</li> <li>• is supported HMI-Standard</li> <li>• is supported HMI-High Feature</li> </ul>  | <ul style="list-style-type: none"> <li>No</li> <li>Yes</li> <li>Yes</li> </ul>  |
| <b>product feature integrated bypass contact system</b>   | Yes   |
| <b>number of controlled phases</b>  | 3   |

|  |   |
|--|---|
| <b>buffering time in the event of power failure</b>          |   |
| • for main current circuit                                   | 100 ms  |
| • for control circuit  | 100 ms  |
| <b>insulation voltage rated value</b>                        | 600 V   |
| <b>degree of pollution</b>                                   | 3, acc. to IEC 60947-4-2  |
| <b>impulse voltage rated value</b>                           | 6 kV  |
| <b>blocking voltage of the thyristor maximum</b>             | 1 600 V   |
| <b>service factor</b>  | 1   |
| <b>surge voltage resistance rated value</b>                  | 6 kV  |
| <b>maximum permissible voltage for protective separation</b> |   |
| • between main and auxiliary circuit                         | 600 V   |
| <b>shock resistance</b>                                      | 15 g / 11 ms, from 12 g / 11 ms with potential contact lifting  |
| <b>vibration resistance</b>                                  | 15 mm to 6 Hz; 2 g to 500 Hz  |
| utilization category according to IEC 60947-4-2              | AC 53a  |
| <b>reference code according to IEC 81346-2</b>               | Q   |
| <b>Substance Prohibitance (day/month/year)</b>               | 02/15/2018  |
| <b>SVHC substance name</b>                                   | Lead CAS-No. 7439-92-1<br>Lead monoxide (lead oxide) CAS-No. 1317-36-8<br>2,2',6,6'-tetrabromo-4,4'-isopropylidenediphenol CAS-No. 79-94-7<br>2-methyl-1-(4-methylthiophenyl)-2-morpholinopropan-1-one CAS-No. 71868-10-5<br>Melamine CAS-No. 108-78-1<br>6,6'-di-tert-butyl-2,2'-methylenedi-p-cresol CAS-No. 119-47-1<br>Dibutylbis(pentane-2,4-dionato-O,O')tin CAS-No. 22673-19-4<br>Diboron trioxide CAS-No. 1303-86-2 |
| <b>Net Weight</b>  | 3.12 kg   |
| <b>product function</b>                                      |   |
| • ramp-up (soft starting)                                    | Yes   |
| • soft stopping  | Yes   |
| • Soft Torque  | Yes   |
| • adjustable current limitation                              | Yes   |
| • pump stop  | Yes   |
| • intrinsic device protection                                | Yes   |
| • motor overload protection                                  | Yes; Full motor protection (thermistor motor protection and electronic motor overload protection)   |
| • evaluation of thermistor motor protection                  | Yes; Type A PTC or Klaxon / Thermoclick   |
| • inside-delta circuit                                       | Yes   |
| • auto-RESET   | Yes   |
| • manual RESET   | Yes   |
| • remote reset   | Yes; By turning off the control supply voltage  |
| • communication function                                     | Yes   |
| • operating measured value display                           | Yes; Only in conjunction with special accessories   |
| • error logbook  | Yes; Only in conjunction with special accessories   |
| • via software parameterizable                               | No  |
| • via software configurable                                  | Yes   |
| • <b>PROFInergy</b>  | Yes; in connection with the PROFINET Standard communication module  |
| • <b>firmware update</b>                                     | Yes   |
| • <b>removable terminal for control circuit</b>              | Yes   |
| • torque control   | No  |
| • analog output  | No  |
| <b>Power Electronics</b>                                     |   |
| <b>operational current</b>                                   |   |
| • at 40 °C rated value                                       | 32 A  |
| • at 50 °C rated value                                       | 28.4 A  |
| • at 60 °C rated value                                       | 26 A  |
| <b>operational current at inside-delta circuit</b>           |   |
| • at 40 °C rated value                                       | 55.4 A  |
| • at 50 °C rated value                                       | 49 A  |
| • at 60 °C rated value                                       | 45 A  |
| <b>operating voltage</b>                                     |   |
| • rated value  | 200 ... 600 V   |

|  |               |
|--|---------------|
| <ul style="list-style-type: none"> <li>• at inside-delta circuit rated value</li> </ul>                                    | 200 ... 600 V |
| <b>relative negative tolerance of the operating voltage</b>  | -15 %         |
| <b>relative positive tolerance of the operating voltage</b>  | 10 %          |
| <b>relative negative tolerance of the operating voltage at inside-delta circuit</b>  | -15 %         |
| <b>relative positive tolerance of the operating voltage at inside-delta circuit</b>  | 10 %          |
| <b>operating power for 3-phase motors</b>  |               |
| <ul style="list-style-type: none"> <li>• at 230 V at 40 °C rated value</li> </ul>  | 7.5 kW        |
| <ul style="list-style-type: none"> <li>• at 230 V at inside-delta circuit at 40 °C rated value</li> </ul>                  | 15 kW         |
| <ul style="list-style-type: none"> <li>• at 400 V at 40 °C rated value</li> </ul>  | 15 kW         |
| <ul style="list-style-type: none"> <li>• at 400 V at inside-delta circuit at 40 °C rated value</li> </ul>                  | 22 kW         |
| <ul style="list-style-type: none"> <li>• at 500 V at 40 °C rated value</li> </ul>  | 18.5 kW       |
| <ul style="list-style-type: none"> <li>• at 500 V at inside-delta circuit at 40 °C rated value</li> </ul>                  | 30 kW         |
| <b>Operating frequency 1 rated value</b>   | 50 Hz         |
| <b>Operating frequency 2 rated value</b>   | 60 Hz         |
| <b>relative negative tolerance of the operating frequency</b>  | -10 %         |
| <b>relative positive tolerance of the operating frequency</b>  | 10 %          |
| <b>adjustable motor current</b>  |               |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 1</li> </ul>                           | 14 A          |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 2</li> </ul>                           | 15.2 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 3</li> </ul>                           | 16.4 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 4</li> </ul>                           | 17.6 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 5</li> </ul>                           | 18.8 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 6</li> </ul>                           | 20 A          |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 7</li> </ul>                           | 21.2 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 8</li> </ul>                           | 22.4 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 9</li> </ul>                           | 23.6 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 10</li> </ul>                          | 24.8 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 11</li> </ul>                          | 26 A          |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 12</li> </ul>                          | 27.2 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 13</li> </ul>                          | 28.4 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 14</li> </ul>                          | 29.6 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 15</li> </ul>                          | 30.8 A        |
| <ul style="list-style-type: none"> <li>• at rotary coding switch on switch position 16</li> </ul>                          | 32 A          |
| <ul style="list-style-type: none"> <li>• minimum</li> </ul>  | 14 A          |
| <b>adjustable motor current</b>  |               |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 1</li> </ul>  | 24.2 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 2</li> </ul>  | 26.3 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 3</li> </ul>  | 28.4 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 4</li> </ul>  | 30.5 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 5</li> </ul>  | 32.6 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 6</li> </ul>  | 34.6 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 7</li> </ul>  | 36.7 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 8</li> </ul>  | 38.8 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 9</li> </ul>  | 40.9 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 10</li> </ul> | 43 A          |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 11</li> </ul> | 45 A          |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 12</li> </ul> | 47.1 A        |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 13</li> </ul> | 49.2 A        |

|  |  |
|--|--|
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 14</li> </ul> | 51.3 A   |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 15</li> </ul> | 53.3 A   |
| <ul style="list-style-type: none"> <li>• for inside-delta circuit at rotary coding switch on switch position 16</li> </ul> | 55.4 A   |
| <ul style="list-style-type: none"> <li>• at inside-delta circuit minimum</li> </ul>  | 24.2 A   |
| <b>minimum load [%]</b>  | 15 %; Relative to smallest settable Ie   |
| <b>power loss [W] for rated value of the current at AC</b>   |  |
| <ul style="list-style-type: none"> <li>• at 40 °C after startup</li> </ul>   | 22 W   |
| <ul style="list-style-type: none"> <li>• at 50 °C after startup</li> </ul>   | 21 W   |
| <ul style="list-style-type: none"> <li>• at 60 °C after startup</li> </ul>   | 20 W   |
| <b>power loss [W] at AC at current limitation 350 %</b>  |  |
| <ul style="list-style-type: none"> <li>• at 40 °C during startup</li> </ul>  | 531 W  |
| <ul style="list-style-type: none"> <li>• at 50 °C during startup</li> </ul>  | 449 W  |
| <ul style="list-style-type: none"> <li>• at 60 °C during startup</li> </ul>  | 395 W  |
| <b>Control circuit/ Control</b>  |  |
| <b>type of voltage of the control supply voltage</b>   | AC   |
| <b>control supply voltage at AC</b>  |  |
| <ul style="list-style-type: none"> <li>• at 50 Hz</li> </ul>   | 110 ... 250 V  |
| <ul style="list-style-type: none"> <li>• at 60 Hz</li> </ul>   | 110 ... 250 V  |
| <b>relative negative tolerance of the control supply voltage at AC at 50 Hz</b>  | -15 %  |
| <b>relative positive tolerance of the control supply voltage at AC at 50 Hz</b>  | 10 %   |
| <b>relative negative tolerance of the control supply voltage at AC at 60 Hz</b>  | -15 %  |
| <b>relative positive tolerance of the control supply voltage at AC at 60 Hz</b>  | 10 %   |
| <b>control supply voltage frequency</b>  | 50 ... 60 Hz   |
| <b>relative negative tolerance of the control supply voltage frequency</b>   | -10 %  |
| <b>relative positive tolerance of the control supply voltage frequency</b>   | 10 %   |
| <b>control supply current in standby mode rated value</b>  | 30 mA  |
| <b>holding current in bypass operation rated value</b>   | 75 mA  |
| <b>inrush current by closing the bypass contacts maximum</b>   | 0.17 A   |
| inrush current peak at application of control supply voltage maximum   | 12.2 A   |
| duration of inrush current peak at application of control supply voltage   | 2.2 ms   |
| <b>design of the overvoltage protection</b>  | Varistor   |
| <b>design of short-circuit protection for control circuit</b>  | 4 A gG fuse (Icu=1 kA), 6 A quick-acting fuse (Icu=1 kA), C1 miniature circuit breaker (Icu= 600 A), C6 miniature circuit breaker (Icu= 300 A); Is not part of scope of supply |
| <b>Inputs/ Outputs</b>   |  |
| <b>number of digital inputs</b>  | 1  |
| <b>number of digital outputs</b>   | 3  |
| <ul style="list-style-type: none"> <li>• not parameterizable</li> </ul>  | 2  |
| <b>digital output version</b>  | 2 normally-open contacts (NO) / 1 changeover contact (CO)  |
| <b>number of analog outputs</b>  | 0  |
| <b>switching capacity current of the relay outputs</b>   |  |
| <ul style="list-style-type: none"> <li>• at AC-15 at 250 V rated value</li> </ul>  | 3 A  |
| <ul style="list-style-type: none"> <li>• at DC-13 at 24 V rated value</li> </ul>   | 1 A  |
| <b>Installation/ mounting/ dimensions</b>  |  |
| <b>mounting position</b>   | with vertical mounting surface +/-90° rotatable, with vertical mounting surface +/- 22.5° tiltable to the front and back   |
| <b>fastening method</b>  | screw fixing   |
| <b>height</b>  | 275 mm   |
| <b>width</b>   | 170 mm   |
| <b>depth</b>   | 152 mm   |
| required spacing with side-by-side mounting  |  |
| <ul style="list-style-type: none"> <li>• forwards</li> </ul>   | 10 mm  |

|   |  |
|---|--|
| <ul style="list-style-type: none"> <li>backwards</li> <li>upwards</li> <li>downwards</li> <li>at the side</li> </ul>  | <p>0 mm</p> <p>100 mm</p> <p>75 mm</p> <p>5 mm</p>   |
| <b>weight without packaging</b>   | 2.3 kg   |
| <b>Connections/ Terminals</b>   |  |
| <b>type of electrical connection</b>  |  |
| <ul style="list-style-type: none"> <li>for main current circuit</li> <li>for control circuit</li> </ul>   | <p>screw-type terminals</p> <p>screw-type terminals</p>  |
| <b>wire length for thermistor connection</b>  |  |
| <ul style="list-style-type: none"> <li>with conductor cross-section = 0.5 mm<sup>2</sup> maximum</li> <li>with conductor cross-section = 1.5 mm<sup>2</sup> maximum</li> <li>with conductor cross-section = 2.5 mm<sup>2</sup> maximum</li> </ul>   | <p>50 m</p> <p>150 m</p> <p>250 m</p>  |
| <b>type of connectable conductor cross-sections</b>   |  |
| <ul style="list-style-type: none"> <li>for main contacts <ul style="list-style-type: none"> <li>— solid</li> <li>— finely stranded with core end processing</li> </ul> </li> <li>for AWG cables for main current circuit solid</li> </ul>   | <p>2x (1.0 ... 2.5 mm<sup>2</sup>), 2x (2.5 ... 10 mm<sup>2</sup>)</p> <p>2x (1.0 ... 2.5 mm<sup>2</sup>), 2x (2.5 ... 6.0 mm<sup>2</sup>)</p> <p>2x (16 ... 12), 2x (14 ... 8)</p>  |
| <b>type of connectable conductor cross-sections</b>   |  |
| <ul style="list-style-type: none"> <li>for control circuit solid</li> <li>for control circuit finely stranded with core end processing</li> <li>for AWG cables for control circuit solid</li> </ul>   | <p>1x (0.5 ... 4.0 mm<sup>2</sup>), 2x (0.5 ... 2.5 mm<sup>2</sup>)</p> <p>1x (0.5 ... 2.5 mm<sup>2</sup>), 2x (0.5 ... 1.5 mm<sup>2</sup>)</p> <p>1x (20 ... 12), 2x (20 ... 14)</p>  |
| <b>wire length</b>  |  |
| <ul style="list-style-type: none"> <li>between soft starter and motor maximum</li> <li>at the digital inputs at AC maximum</li> </ul>   | <p>800 m</p> <p>100 m</p>  |
| <b>tightening torque</b>  |  |
| <ul style="list-style-type: none"> <li>for main contacts with screw-type terminals</li> <li>for auxiliary and control contacts with screw-type terminals</li> </ul>   | <p>2 ... 2.5 N·m</p> <p>0.8 ... 1.2 N·m</p>  |
| <b>tightening torque [lbf·in]</b>   |  |
| <ul style="list-style-type: none"> <li>for main contacts with screw-type terminals</li> <li>for auxiliary and control contacts with screw-type terminals</li> </ul>   | <p>18 ... 22 lbf·in</p> <p>7 ... 10.3 lbf·in</p>   |
| <b>Ambient conditions</b>   |  |
| installation altitude at height above sea level maximum   | 5 000 m  |
| <b>ambient temperature</b>  |  |
| <ul style="list-style-type: none"> <li>during operation</li> <li>during storage and transport</li> </ul>  | <p>-25 ... +60 °C; Please observe derating at temperatures of 40 °C or above</p> <p>-40 ... +80 °C</p>   |
| <b>environmental category</b>   |  |
| <ul style="list-style-type: none"> <li>during operation according to IEC 60721</li> <li>during storage according to IEC 60721</li> <li>during transport according to IEC 60721</li> </ul>   | <p>3K6 (no ice formation, only occasional condensation), 3C3 (no salt mist), 3S2 (sand must not get into the devices), 3M6</p> <p>1K6 (only occasional condensation), 1C2 (no salt mist), 1S2 (sand must not get inside the devices), 1M4</p> <p>2K2, 2C1, 2S1, 2M2 (max. fall height 0.3 m)</p>                             |
| <b>Electromagnetic compatibility</b>  |  |
| <b>EMC emitted interference</b>   | acc. to IEC 60947-4-2: Class A   |
| <b>Communication/ Protocol</b>  |  |
| <b>communication module is supported</b>  |  |
| <ul style="list-style-type: none"> <li>PROFINET standard</li> <li>EtherNet/IP</li> <li>Modbus RTU</li> <li>Modbus TCP</li> <li>PROFIBUS</li> </ul>  | <p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p> <p>Yes</p>   |
| <b>UL/CSA ratings</b>   |  |
| <b>manufacturer's article number</b>  |  |
| <ul style="list-style-type: none"> <li>of circuit breaker usable for Standard Faults <ul style="list-style-type: none"> <li>— at 460/480 V according to UL</li> <li>— 60/480 V according to UL</li> <li>— at 460/480 V at inside-delta circuit according to UL</li> <li>— 60/480 V at inside-delta circuit according to UL</li> </ul> </li> </ul> | <p>Siemens type: 3RV2742, max. 70 A or 3VA51, max. 100 A; I<sub>q</sub> = 5 kA</p> <p>Siemens type: 3RV2742, max.40 A or 3VA51, max. 60 A; I<sub>q</sub> max = 65 kA</p> <p>Siemens type: 3RV2742, max. 70 A or 3VA51, max. 100 A; I<sub>q</sub> = 5 kA</p> <p>Siemens type: 3VA51, max. 60 A; I<sub>q</sub> max = 65 kA</p> |

- at 575/600 V according to UL
- at 575/600 V at inside-delta circuit according to UL

● of the fuse

- usable for Standard Faults up to 575/600 V according to UL
- usable for High Faults up to 575/600 V according to UL
- usable for Standard Faults at inside-delta circuit up to 575/600 V according to UL
- usable for High Faults at inside-delta circuit up to 575/600 V according to UL

Siemens type: 3RV2742, max. 70 A or 3VA51, max. 100 A; Iq = 5 kA  
 Siemens type: 3RV2742, max. 70 A or 3VA51, max. 100 A; Iq = 5 kA

Type: Class RK5 / K5, max. 125 A; Iq = 5 kA

Type: Class J / L, max. 125 A; Iq = 100 kA

Type: Class RK5 / K5, max. 125 A; Iq = 5 kA

Type: Class J / L, max. 125 A; Iq = 100 kA

**operating power [hp] for 3-phase motors**

- at 200/208 V at 50 °C rated value
- at 220/230 V at 50 °C rated value
- at 460/480 V at 50 °C rated value
- at 575/600 V at 50 °C rated value
- at 200/208 V at inside-delta circuit at 50 °C rated value
- at 220/230 V at inside-delta circuit at 50 °C rated value
- at 460/480 V at inside-delta circuit at 50 °C rated value
- at 575/600 V at inside-delta circuit at 50 °C rated value

7.5 hp  
 10 hp  
 20 hp  
 25 hp  
 15 hp  
 15 hp  
 30 hp  
 40 hp

**contact rating of auxiliary contacts according to UL**

R300-B300

Electrical Safety

**protection class IP on the front according to IEC 60529**

IP20

**touch protection on the front according to IEC 60529**

finger-safe, for vertical contact from the front

**Approvals Certificates**

Environmental Product Declaration

- global warming potential [CO2 eq] / during manufacturing 37.2 kg
- global warming potential [CO2 eq] / during sales 0.66 kg
- global warming potential [CO2 eq] / during operation 152 kg
- global warming potential [CO2 eq] / after end of life -4.19 kg
- global warming potential [CO2 eq] / total 185 kg

Environment

General Product Approval

[Environmental Confirmations](#)



General Product Approval

EMV

Test Certificates

Maritime application



[Type Test Certificates/Test Report](#)



Maritime application

other



[Confirmation](#)

[Confirmation](#)

other



**Further information**

Information on the packaging

