

Standard terminal blocks

Compression clamp

 **DIN 1 - 3**

Test connector : See Accessories section

End stop	th. 9 mm	BADL V0	0199 408.02
End stop	th. 9,1 mm	BAM	0103 002.26
Rail	35 x 7,5 x 1	PR30 prepunched	0173 220.05
Rail	35 x 15 x 2,3	PR4	0168 500.12
Rail	35 x 15 x 1,5	PR5 prepunched	0101 598.26
Rail	32 x 15 x 1,5	PR1Z2	0163 050.04

Other end stops and rails : See Accessories section

Characteristics

Wire size

		IEC		UL	CSA
		NFC	DIN		
Compression clamp	Solid wire	0,5-10 mm ²	24-8 AWG	24-8 AWG	
	Stranded wire	0,5-6 mm ²	24-8 AWG	24-8 AWG	

Voltage

Rated	800 V	600 V	600 V
Pulse	8 kV		
Pollution degree	3		

Current

Rated	41 A	50 A	55 A
-------	------	------	------

Wire size

Rated / Gauge	6 mm ² / A5	8 AWG	8 AWG
Wire stripping length	Recomm. Screwdriver	Recomm. torque	Protection
12 mm	4-5 mm	0,8-1 Nm	IP 20
.47"	.157"-.197"	7.1-8.9 lb.in.	NEMA 1

Notes

The use of some accessories may decrease the block's voltage rating. For more information, consult us.


BJDP1 permits the interconnection with a terminal block series "M" spacing 16 mm.

BJDP3 permits the interconnection with a terminal block series "M" spacing 12 mm.

BJDP5 permits the interconnection with a terminal block series "M" spacing 10 mm.

M 6/8.2A.G

Spacing 8 mm - 0,05 (.315")




Grey  **0115 672.24**

Standard 8 mm block with a partition and a central quick-connect output for 2,8 x 0,8 mm series 110 tabs.

M 6/8...

Spacing 8 mm - 0,05 (.315")



Standard 8 mm block.

0115 118.11



Accessories

1	End section	grey	FEM6	th. 2,8 mm	0118 368.16
2		blue	FEM6	th. 2,8 mm	0128 368.10
3		orange	FEM6	th. 2,8 mm	0103 126.16
4		yellow	FEM6	th. 2,8 mm	0103 062.21
5		green	FEM6	th. 2,8 mm	0103 125.15
6		white	FEM6	th. 2,8 mm	0103 312.20
7		beige	FEM6 V0	V0 th. 2,8 mm	0198 368.17
8		blue	FEM6 V0	V0 th. 2,8 mm	0199 302.07
9		yellow	FEM6 V0	V0 th. 2,8 mm	0199 305.02
10	End section	grey	FEM61	(3) th. 3,0 mm	0114 776.23
11	End section	grey	FEM6C	(3) th. 3,0 mm	0114 777.24
12	Separator end section	grey	SCM6		0113 003.10
13	Separator end section	blue	SCM6		0123 003.12
14	Separator end section	beige	SCM6 V0	V0	0193 003.11
15	Separator end section	grey	SCF6	th. 3,0 mm	0118 707.03
16	Separator end section	blue	SCF6	th. 3,0 mm	0128 707.05
17	Separator end section	beige	SCF6 V0	V0 th. 3,0 mm	0198 707.04
18	Separator end section	grey	SCF61	th. 3,0 mm	0114 202.25
19	Separator end section	grey	SCFM6	(3) th. 3,0 mm	0114 825.05
20	Separator end section	grey	SCFEX1	(3) th. 2,4 mm	0103 619.04
21	Separator end section	grey	SCFEX3	(3) th. 2,4 mm	0103 620.01
22	Separator end section (for cover CPV)	grey	SCFCV1-2	th. 3,0 mm	0116 795.11
23	Protective cover	beige	SCFCV1-2 V0	V0 th. 3,0 mm	0196 795.12
24	Protective cover		CPM	(for FEM6C, SCF6(V0) and SCFM6)	0187 312.14
25	Test socket		CPV1-2	(for SCFCV1-2...)	0176 816.12
26	Test device		AL2	(1) DIA. 2 mm	0163 043.21
27	Test plug		AL3	(1) DIA. 3 mm	0163 261.00
28			AL4	(1) DIA. 4 mm	0163 262.01
29			DCO	orange	0173 060.00
30			FC2	DIA. 2 mm	0007 865.26
31			FC4	DIA. 4 mm	0167 860.01
32	Assembled jumper bar	41 A	BJM8	(1) 2 poles	0168 520.05
33	Assembled jumper bar (without IP20 protection)	41 A	BJM8	(1) 3 poles	0168 521.22
34		41 A	BJM8	(1) 4 poles	0168 522.23
35		41 A	BJM8	(1) 5 poles	0168 523.24
36		41 A	BJM8	(1) 10 poles	0168 974.00
37	Assembled jumper bar (with IP20 protection)	41 A	BJMI8	(1) 2 poles	0176 669.16
38		41 A	BJMI8	(1) 3 poles	0176 670.13
39		41 A	BJMI8	(1) 4 poles	0176 671.00
40		41 A	BJMI8	(1) 5 poles	0176 672.01
41		41 A	BJMI8	(1) 10 poles	0176 673.02
42	Jumper bar not assembled (Post + washer + captive screw)	41 A	BJS8	(1) 20 poles	0174 789.05
43	Connector plate	35 A	EV6		0168 604.16
44	Screwless jumper bar orange IP 20	41 A	EL6		0173 627.21
45		41 A	BE8.2	(4) 2 poles	0299 712.05
46		41 A	BE8.3	(4) 3 poles	0299 713.06
47		41 A	BE8.4	(4) 4 poles	0299 714.07
48		41 A	BE8.5	(4) 5 poles	0299 715.00
49		41 A	BE8.10	(4) 10 poles	0299 720.11
50	Jumper		BJB		0199 466.23
51	Pivoting jumper bar	50 A	BJP8		0174 448.07
52	Universal jumper bar	50 A	BJDP1	(1)(2) spacing 8 <-> spacing 16	0179 623.03
53		70 A	BJDP3	(1)(2) spacing 8 <-> spacing 12	0179 625.05
54		50 A	BJDP5	(1)(2) spacing 8 <-> spacing 10	0174 782.26
55	Comb type jumper bar	50 A	PC8	(4) 2 poles	0116 538.17
56		50 A	PC8	(4) 10 poles	0163 313.24
57	Bridging plug		BP8.A4		0173 888.20
58	Protection label		EP6	3 blocks	0163 427.17
59			EP8	4 blocks	0163 428.20
60	Screw for protection label		VSP6		0163 433.15
61	Protection label		EPU6		0107 038.25
62	IDC jumper		AD2,5		0114 205.20

R See section on markers marking method

Note : (1) A circuit separator SC may be required with the use of these accessories. (2) See "Notes". (3) End sections and separators snapped on rails. (4) See section : "Accessories" for other configurations of poles.