

Single Bipolar Transistor multicomp^{PRO}

RoHS
Compliant



Features

- High voltage transistor
- Low collector-emitter saturation voltage

Absolute Maximum Ratings $T_a = 25^\circ\text{C}$

Parameter	Symbol	Rating	Unit
Collector - Base Voltage	V_{CBO}	-300	V
Collector-Emitter Voltage	V_{CEO}		
Emitter - Base Voltage	V_{EBO}	-5	
Collector Current - Continuous	I_C	-500	mA
Collector Power Dissipation	P_C	350	mW
Thermal Resistance From Junction To Ambient	$R_{\theta JA}$	417	$^\circ\text{C/W}$
Junction Temperature	T_J	150	$^\circ\text{C}$
Storage temperature range	T_{stg}	-55 to +150	

Electrical Characteristics $(T_a = 25^\circ\text{C})$

Parameter	Symbol	Test Conditions	Min	Max	Unit
Collector-Base Breakdown Voltage	V_{CBO}	$I_C = -100\ \mu\text{A}, I_E = 0$	-300		V
Collector-Emitter Breakdown Voltage	V_{CEO}	$I_C = -1\text{mA}, I_B = 0$			
Emitter-Base Breakdown Voltage	V_{EBO}	$I_E = -100\ \mu\text{A}, I_C = 0$	-5		
Collector-base cut-off current	I_{CBO}	$V_{CB} = 200\text{V}, I_E = 0$		-0.25	μA
Emitter cut-off current	I_{EBO}	$V_{EB} = -5\text{V}, I_C = 0$		-0.1	
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = -20\text{mA}, I_B = -2\text{mA}$		-0.2	V
Base-Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C = -20\text{mA}; I_B = -2\text{mA}$		-0.9	
DC current gain	$h_{FE(1)}$	$V_{CE} = -10\text{V}, I_C = -1\text{mA}$	60		
	$h_{FE(2)}$	$V_{CE} = -10\text{V}, I_C = -10\text{mA}$	100	300	
	$h_{FE(3)}$	$V_{CE} = -10\text{V}, I_C = -30\text{mA}$	60		
Transition frequency	f_T	$V_{CE} = -20\text{V}, I_C = 10\text{mA}, f = 30\text{MHz}$	50		MHz

Classification of $h_{FE(2)}$


Type	MMBTA92
Range	100-300
Marking	2D

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
sg.element14.com/b/multicomp-pro


multicom^{PRO}

Single Bipolar Transistor multicom^{PRO}

Typical Characteristics



Diagram



Part Number Table

Description	Part Number
Single Bipolar Transistor, PNP, -0.5A, -300V, SOT 23	MMBTA92

Dimensions : Millimetres

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicom Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicom-pro
Farnell.com/multicom-pro
sg.element14.com/b/multicom-pro

multicom^{PRO}