

[Download Instructions \(Americas\)](#)
[Download Instructions \(Rest of World\)](#)

Basic Charger / Base Charger

ECONOMICAL

- Most affordable Energizer® charger



EASY TO USE

- Lights indicate batteries are charging



CONVENIENT

- Charges 2 or 4 NiMH batteries



Product Detail:

Designation: Basic Charger / Base Charger

Model: CHVC4E / CHVC4

Color: Black

Charge Capability: "AA" (2) or (4) / "AAA" (2) or (4)
 "AA" (2) and "AAA" (2) Simultaneously

Note: When charging only 2 batteries, place batteries in the two positions to the left or right.

Charging Times: (estimated)	Battery	Capacity	Estimated
	(NiMH)	(mAh)	(time)
	AA	1300-2000	8-11 hrs
	AA	2000-2300	11-13 hrs
	AAA	500-800	7-10 hrs

Shutoff Mechanism: (CHVC4E) Timer Control: 15 hours
 (CHVC4) None

Charging Current: "AA" 170-200mA
 "AAA" 80-100mA

Trickle Charge: None

Input Rating (CHVC4E): 110V-127VAC, 50-60Hz, 6W

Input Rating (CHVC4): 220V-240VAC, 50-60Hz, 6W

Typical Weight: 88 grams

Dimensions (mm): 105 x 70 x 70 (H x L x W)

Safety Features: Reverse Polarity Protection

Before Using Your Charger:

Please read all instructions and cautionary markings on the battery charger, batteries, and device.

Best used with Energizer® NiMH batteries.

Important Notice

This datasheet contains information specific to products manufactured at the time of its publication.

Contents herein do not constitute a warranty.

Energizer.