

R45C IO-Link to Dual Analog Input-Output Converter Quick Start Guide



Features

This guide is designed to help you set up and install the R45C IO-Link to Dual Analog Input-Output Converter. For complete information on programming, performance, troubleshooting, dimensions, and accessories, please refer to the Instruction Manual at www.bannerengineering.com. Search for part number 228480 to view the Instruction Manual. Use of this document assumes familiarity with pertinent industry standards and practices.

Overview

Analog In When this converter receives an analog input value, the numerical representational value is sent to an IO-Link Master via Process Data In (PDI). PDI Analog Ranges: - Voltage = 0 mV to 10,000 mV - Current = 4,000 μA to 20,000 μA	Analog Out This converter also allows for the user to output an analog value by sending the numerical analog value from the IO-Link Master via Process Data Out (PDO). PDO Analog Ranges: - Voltage = 0 mV to 11,000 mV - Current = 0 μA to 24,000 μA
PDO Outside Valid Range (POVR) If the PDO value sent to this converter is outside of the PDO Analog Range value, then the actual analog output value will be set to one of the three selectable POVR levels after a 2-second delay: - Low (default): 0 V or 3.5 mA - High: 10.5 V or 20.5 mA - Hold: Level retains previous value indefinitely NOTE: If a connected IO-Link sensor is changed back to SIO mode, then the previous value will be held.	PFM Out Enables a PFM representation of an analog input as an output. PFM Input Source Channel Selects the analog input value from Port 1 or Port 2 as the PFM output source. Pulse Frequency Configuration Sets the near and far frequency values.

Status Indicators

The R45C IO-Link to Dual Analog Input-Output Converter has four amber LED indicators on both sides for IO-Link and analog communications to allow for installation needs and still provide adequate indication visibility. There is also a green LED indicator on both sides of the converter, which signals the device's power status.

IO-Link Amber LED	
Indication	Status
Off	IO-Link communications are not present
Flashing Amber (900 ms On, 100 ms Off)	IO-Link communications are active

Analog In Amber LED	
Indication	Status
Off	Analog current value is less than setpoint SP1 OR analog value is greater than setpoint SP2
Solid Amber	Analog current value is between setpoint SP1 AND setpoint SP2
Default Current Values: - SP1 = 0.004 A - SP2 = 0.02 A	Default Voltage Values: - SP1 = 0 V - SP2 = 10 V

Analog Out Amber LED	
Indication	Status
Off	Turns off if written PDO analog value is outside the allowable output range
Solid Amber	Turns on if written PDO analog value is inside the allowable output range
Allowable Current Range: 0 mA to 24 mA	
Allowable Voltage Range: 0 V to 11 V	

Mechanical Installation

Install the R45C to allow access for functional checks, maintenance, and service or replacement. Do not install the R45C in such a way to allow for intentional defeat.

Fasteners must be of sufficient strength to guard against breakage. The use of permanent fasteners or locking hardware is recommended to prevent the loosening or displacement of the device. The mounting hole (4.5 mm) in the R45C accepts M4 (#8) hardware.



CAUTION: Do not overtighten the R45C's mounting screw during installation. Overtightening can affect the performance of the R45C.

Specifications

Supply Voltage

18 V DC to 30 V DC at 50 mA maximum

Power Pass-Through Current

4 A maximum

Analog Input Impedance

Current version: Approximately 250 ohms

Voltage version: Approximately 14.3K ohms

Analog Output Load Resistance

Current version: 1 kilo-ohm maximum load resistance at 24 V DC

Maximum Load Resistance = $[(V_{CC} - 4.5) + 0.02 \text{ ohms}]$

Voltage version: 2.5 kilo-ohms minimum load resistance

Supply Protection Circuitry

Protected against reverse polarity and transient voltages

Leakage Current Immunity

400 μ A

Accuracy

0.5%

Indicators

Green: Power

Amber: IO-Link communications

Amber: Analog input value present

Amber: Analog output value in range

Vibration and Mechanical Shock

Meets IEC 60068-2-6 requirements (Vibration: 10 Hz to 55 Hz, 0.5 mm amplitude, 5 minutes sweep, 30 minutes dwell)

Meets IEC 60068-2-27 requirements (Shock: 15G 11 ms duration, half sine wave)


Certifications



Banner Engineering BV
Park Lane, Culliganlaan 2F bus 3
1831 Diegem, BELGIUM



Turck Banner LTD Blenheim House
Blenheim Court
Wickford, Essex SS11 8YT
GREAT BRITAIN



Resolution

14 bits

Connections

Integral 4-pin M12 male/female M12 quick-disconnect connector

Construction

Coupling Material: Nickel-plated brass
Connector Body: PVC translucent black

Environmental Rating

IP65, IP67, IP68

UL Type 1

Operating Conditions

Temperature: -40 °C to +60 °C (-40 °F to +140 °F)

90% at +60 °C maximum relative humidity (non-condensing)

Storage Temperature: -40 °C to +80 °C (-40 °F to +176 °F)

Required Overcurrent Protection



WARNING: Electrical connections must be made by qualified personnel in accordance with local and national electrical codes and regulations.

Overcurrent protection is required to be provided by end product application per the supplied table. Overcurrent protection may be provided with external fusing or via Current Limiting, Class 2 Power Supply.

Supply wiring leads < 24 AWG shall not be spliced. For additional product support, go to www.bannerengineering.com.

Supply Wiring (AWG)	Required Overcurrent Protection (A)	Supply Wiring (AWG)	Required Overcurrent Protection (A)
20	5.0	26	1.0
22	3.0	28	0.8
24	1.0	30	0.5

Banner Engineering Corp Limited Warranty

Banner Engineering Corp. warrants its products to be free from defects in material and workmanship for one year following the date of shipment. Banner Engineering Corp. will repair or replace, free of charge, any product of its manufacture which, at the time it is returned to the factory, is found to have been defective during the warranty period. This warranty does not cover damage or liability for misuse, abuse, or the improper application or installation of the Banner product.

THIS LIMITED WARRANTY IS EXCLUSIVE AND IN LIEU OF ALL OTHER WARRANTIES WHETHER EXPRESS OR IMPLIED (INCLUDING, WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE), AND WHETHER ARISING UNDER COURSE OF PERFORMANCE, COURSE OF DEALING OR TRADE USAGE.

This Warranty is exclusive and limited to repair or, at the discretion of Banner Engineering Corp., replacement. **IN NO EVENT SHALL BANNER ENGINEERING CORP. BE LIABLE TO BUYER OR ANY OTHER PERSON OR ENTITY FOR ANY EXTRA COSTS, EXPENSES, LOSSES, LOSS OF PROFITS, OR ANY INCIDENTAL, CONSEQUENTIAL OR SPECIAL DAMAGES RESULTING FROM ANY PRODUCT DEFECT OR FROM THE USE OR INABILITY TO USE THE PRODUCT, WHETHER ARISING IN CONTRACT OR WARRANTY, STATUTE, TORT, STRICT LIABILITY, NEGLIGENCE, OR OTHERWISE.**

Banner Engineering Corp. reserves the right to change, modify or improve the design of the product without assuming any obligations or liabilities relating to any product previously manufactured by Banner Engineering Corp. Any misuse, abuse, or improper application or installation of this product or use of the product for personal protection applications when the product is identified as not intended for such purposes will void the product warranty. Any modifications to this product without prior express approval by Banner Engineering Corp will void the product warranties. All specifications published in this document are subject to change; Banner reserves the right to modify product specifications or update documentation at any time. Specifications and product information in English supersede that which is provided in any other language. For the most recent version of any documentation, refer to: www.bannerengineering.com.

For patent information, see www.bannerengineering.com/patents.

Document title: R45C IO-Link to Dual Analog Input-Output Converter Quick Start Guide

Part number: 228479

Revision: B

Original Instructions

© Banner Engineering Corp. All rights reserved.



228479