

Monitoring Relays

1-Phase True RMS AC/DC Over or Under Current

Types DIB01, PIB01

CARLO GAVAZZI



DIB01



PIB01

- TRMS AC/DC over or under current monitoring relay
- Current measuring through internal shunt
- Selection of measuring range by DIP-switches
- Measuring ranges from 0.1 mA to 10 A AC/DC
- Adjustable current on relative scale
- Adjustable hysteresis on relative scale
- Adjustable delay function (0.1 to 30 s)
- Programmable latching or inhibit at set level
- Output: 8 A SPDT relay N.D. or N.E. selectable
- For mounting on DIN-rail in accordance with DIN/EN/EC 60715 (DIB01) or plug-in module (PIB01)
- 22.5 mm Euronorm housing (DIB01) or 36 mm plug-in module (PIB01)
- LED indication for relay, alarm and power supply ON
- Galvanically separated power supply

Product Description

DIB01 and PIB01 are precise TRMS AC/DC over or under current (selectable by DIP-switch) monitoring relays. Direct measuring or through current transformer. Owing to the built-in latch function, the ON-position of the relay output can be maintained. Inhibit function

can be used to avoid relay operation when not desired (maintenance, transitions). The LED's indicate the state of the alarm and the output relay. Through the built-in shunt it is possible to monitor loads up to 10 A AC/DC.

Ordering Key

DIB 01 C B23 5A

Housing _____
 Function _____
 Type _____
 Item number _____
 Output _____
 Power supply _____
 Measuring range _____

Type Selection

Mounting	Output	Measuring range	Supply: 24 to 48 VAC/DC	Supply: 115/230 VAC
DIN-rail	SPDT	0.1 to 5 mA AC/DC 1 to 50 mA AC/DC 10 to 500 mA AC/DC 0.1 to 5 A AC/DC 1 to 10 A AC/DC	DIB 01 C D48 5mA DIB 01 C D48 50mA DIB 01 C D48 500mA DIB 01 C D48 5A DIB 01 C D48 10A	DIB 01 C B23 5mA DIB 01 C B23 50mA DIB 01 C B23 500mA DIB 01 C B23 5A DIB 01 C B23 10A
Plug-in	SPDT	0.1 to 5 mA AC/DC 1 to 50 mA AC/DC 10 to 500 mA AC/DC 0.1 to 5 A AC/DC 1 to 10 A AC/DC	PIB 01 C D48 5mA PIB 01 C D48 50mA PIB 01 C D48 500mA PIB 01 C D48 5A PIB 01 C D48 10A	PIB 01 C B23 5mA PIB 01 C B23 50mA PIB 01 C B23 500mA PIB 01 C B23 5A PIB 01 C B23 10A

Input Specifications

Input (current level)	Terminals Y1, Y2	Terminals 5, 7	Measuring ranges (cont.)	Internal resist.	Max. curr.
DIB01					
PIB01					
Measuring ranges	Internal resist.	Max. curr.			
Direct					
Selectable by DIP-switch					
..5MA: 0.1 to 1 mA AC/DC	50 Ω	50 mA	..500MA: 10 to 100 mA AC/DC	0.5 Ω	700 mA
0.2 to 2 mA AC/DC	50 Ω	50 mA	20 to 200 mA AC/DC	0.5 Ω	700 mA
0.5 to 5 mA AC/DC	50 Ω	50 mA	50 to 500 mA AC/DC	0.5 Ω	700 mA
Max. current for 1 s		100 mA	Max. current for 1 s		1.4 A
..50MA: 1 to 10 mA AC/DC	5 Ω	150 mA	..5A: 0.1 to 1 A AC/DC	0.05 Ω	6 A
2 to 20 mA AC/DC	5 Ω	150 mA	0.2 to 2 A AC/DC	0.05 Ω	6 A
5 to 50 mA AC/DC	5 Ω	150 mA	0.5 to 5 A AC/DC	0.05 Ω	6 A
Max. current for 1 s		500 mA	Max. current for 1 s		15 A
			..10A: 1 to 10 A AC/DC	3 mΩ	11 A
			Max. current for 1 s		50 A

Input Specifications (cont.)

Measuring ranges (cont.)

Standard CT (examples)	AAC _{rms}	Max. curr.
TADK2 50 A/5 A	5 to 50 A	60 A
CTD1 150 A/5 A	15 to 150 A	180 A
CTD4 400 A/5 A	40 to 400 A	480 A
TAD12 1000 A/5 A	100 to 1000 A	1200 A
TACO200 6000 A/5 A	600 to 6000 A	7200 A

Note:

The input voltage cannot raise over 300 VAC/DC with respect to ground (PIB01 only)

Contact input

DIB01	Terminals Z1, Y1
PIB01	Terminals 8, 9
Disabled	> 10 kΩ
Enabled	< 500 Ω
Latch disable	> 500 ms

Output Specifications

Output	SPDT relay
Rated insulation voltage	250 VAC
Contact ratings	μ
Resistive loads AC 1	8 A @ 250 VAC
DC 12	5 A @ 24 VDC
Small inductive loads AC 15	2.5 A @ 250 VAC
DC 13	2.5 A @ 24 VDC
Mechanical life	≥ 30 x 10 ⁶ operations
Electrical life	≥ 50 x 10 ³ operations (at 8 A, 250 V, cos φ = 1)
Dielectric strength	
Dielectric voltage	≥ 2 kVAC (rms)
Rated impulse withstand volt.	4 kV (1.2/50 μs)

Supply Specifications

Power supply	Overvoltage cat. III (IEC 60664, IEC 60038)	DC supply	AC supply
Rated operational voltage through terminals:		2 kV	4 kV
A1, A2 or A3, A2 (DIB01)		4 kV	4 kV
2, 10 or 11, 10 (PIB01)		4 kV	4 kV
D48:	24 to 48 VAC/DC ± 15%		
	45 to 65 Hz, insulated		
B23:	115/230 VAC ± 15%		
	45 to 65 Hz, insulated		
Dielectric voltage		Rated operational power	
Supply to input		AC	4 VA
Supply to output		DC	0.8 W
Input to output			

General Specifications

Power ON delay	1 s ± 0.5 s or 6 s ± 0.5 s	Housing	
Reaction time	(input signal variation from -20% to +20% or from +20% to -20% of set value)	Dimensions	DIB01 22.5 x 80 x 99.5 mm PIB01 36 x 80 x 94 mm
Alarm ON delay	< 100 ms	Material	Polyamide (Nylon) or Phenylene ether + Polystyrene
Alarm OFF delay	< 100 ms	Weight	Approx. 150 g
Accuracy	(15 min warm-up time)	Screw terminals	
Temperature drift	± 1000 ppm/°C	Tightening torque	Max. 0.5 Nm acc. to IEC 60947
Delay ON alarm	± 10% on set value ± 50 ms	Product standard	EN 60255-6
Repeatability	± 0.5% on full-scale	Approvals	UL, CSA CCC (GB/T14048.5) only DIB
Indication for		CE Marking	L.V. Directive 2006/95/EC EMC Directive 2004/108/EC
Power supply ON	LED, green	EMC	
Alarm ON	LED, red (flashing 2 Hz during delay time)	Immunity	According to EN 60255-26 According to EN 61000-6-2
Output relay ON	LED, yellow	Emissions	According to EN 60255-26 According to EN 61000-6-3
Environment	(EN 60529)		
Degree of protection	IP 20		
Pollution degree	2		
Operating temperature	-20 to 60°C, R.H. < 95%		
Storage temperature	-30 to 80°C, R.H. < 95%		

Mode of Operation

DIB01 and PIB01 monitor both AC and DC over or under current through an internal shunt.

Example 1

(connection between terminals Z1, Y1 or 8, 9 - latching function enabled)

The relay operates and latches in operating position when the measured value

exceeds (or drops below) the set level for more than the set delay time. Provided that the current has dropped below (or has exceeded) the set point (see hysteresis setting), the relay releases when the interconnection between terminals Z1, Y1 or 8, 9 is interrupted or the power supply is interrupted as well.

The red LED flashes until the

delay time has expired or the measured value comes back to a non-alarm value (see hysteresis setting).

Example 2 (Standard CT)

(no connection between terminals Z1, Y1 or 8, 9 - latch function disabled)

The relay operates when the measured value exceeds (or drops below) the set

level for more than the set delay time. It releases when the current drops below (or exceeds) the set level (see hysteresis setting) or when power supply is interrupted.

Note

When the inhibit contact is opened, if the input signal is already in alarm position, the delay time needs to elapse before relay activation.

Function/Range/Level and Time Delay Setting

Adjust the input range setting the DIP switches 1 and 2 as shown below (except for models DIB01xxx10A and PIB01xxx10A). Select the desired function setting the DIP switches 3 to 6 (1 to 4 for DIB01xxx10A and PIB01xxx10A) as shown below.

To access the DIP switches open the grey plastic cover as shown below.

Selection of level and time delay:

Upper knob:


Setting of hysteresis on relative scale: 0 to 30% on set value.

Centre knob:

Current level setting on relative scale: 10 to 110% on full scale.

Lower knob:


Setting of delay on alarm time on absolute scale (0.1 to 30 s).






Operation Diagrams


Over current - N.D. relay




Under current - Latch function - N.D. relay





Under current - N.D. relay




Over current - Inhibit function - N.D. relay



Wiring Diagrams



Dimensions

DIN-rail**Plug-in**