

## LED Dimming Driver 12vdc/24vdc 8A max

### Part number LED-DIAL-DIMMER

- Input voltage: DC 12V / 24V
- Output voltage: Same as input voltage
- Output power: 8A (Maximum 96W at 12vdc / Maximum 192W at 24vdc)
- Output Signal PWM
- Simply turn dial to increase or decrease brightness of LED strip (or similar constant voltage luminaire)
- No battery required
- A constant voltage power supply will be needed to provide the 12vdc or 24vdc input. The output voltage supplied by this unit will be the same as the input voltage so make sure the correct PSU is selected for your LED strip
- Dimensions: 89 x 59 x 65mm

