Schottky Rectifier





Features

· Low forward voltage drop

· High current capability

High reliability

· High surge current capability

Mechanical Data:

Case : Moulded plastic DO-201AD

Lead : Axial leads, solderable per MIL-STD-202, Method 208 guaranteed

Polarity : Colour band denotes cathode end

High Temperatures

Soldering Guaranteed : 260°C / 10 seconds / 0.375 inches (9.5mm) lead lengths at 5 lbs.,

(2.3 kg) tension

Maximum Ratings and Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified. Single phase, half wave, 60 Hz, resistive or inductive load. For capacitive load, derate current by 20%

Parameter	Symbol	1N5820+	1N5821+	1N5822+	Unit	
Maximum Repetitive Peak Reverse Voltage	VRRM	20	30 40			
Maximum RMS Voltage	VRMS	14	14 21 28 \\ 20 30 40			
Maximum DC Blocking Voltage	VDC	20				
Maximum Average Forward Rectified Current 0.375 Inches (9.5 mm) Lead Length at T _L = 90°C	l(AV)	,			- A	
Peak Forward Surge Current, 8.3 ms Single Half Sine-wave Superimposed on Rated Load (JEDEC method)	IFSM					
Maximum Instantaneous Forward Voltage at 3A	VF	0.475	0.5	0.525	V	
Maximum Instantaneous Forward Voltage at 9A	\ \frac{\fir}{\fin}}}}}}}}}}{\frac{\frac{\frac{\frac{\frac{\frac{\frac{\fir}}}}{\firac{\firac{\fir}{\firac{\fir}}}}}{\firac{\firac{\fir}{\firac{\fir}}}}}}{\frac{\frac{	0.85	0.9	0.95	v	
Maximum DC Reverse Current at T _A = 25°C at Rated DC Blocking Voltage at T _A = 100°C	lR	2 20			mA	
Typical Thermal Resistance (Note 1)	Røja	40			°C/W	
Typical Junction Capacitance (Note 2)	CJ	200			pF	
Operating Temperature Range	TJ	-65 to + 125			°C	
Storage Temperature Range	Тѕтс					

Notes:

- 1. Mount on Cu-Pad Size 16 × 16 mm on PCB
- 2. Measured at 1 MHz and applied reverse voltage of 4 V DC

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro



Schottky Rectifier





Specification Table


I _{F(av)} Maximum (A)	V _{RRM} Maximum (V)	V _F (V) at I _F = 1A	Iғsм (А)	Length	Diameter	Package	Part Number
	20	0.47	80	9.5	5.6	DO-201AD	1N5820+
3	30	0.5					1N5821+
	40	0.52					1N5822+

Dimensions: Millimetres

Ratings and Characteristic Curves







20 Instantaneous Forward Current (mA) 1N5820 Tj = 25°C Pulse Width = 300 µs 1% Duty Cycle Forward Voltage (V)


Figure 4 Typical Forward Characteristics

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro




Schottky Rectifier





Dimensions:



Dimensions: Inches (Millimetres)

Part Number Table

Description	Part Number		
Schottky Rectifier, 20V, 3A	1N5820+		
Schottky Rectifier, 30V, 3A	1N5821+		
Schottky Rectifier, 40V, 3A	1N5822+		

Important Notice: This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro Farnell.com/multicomp-pro Element14.com/multicomp-pro

