

Security

Strobe Lights

SL-126Q 6 to 12 Volt Use

SL-126-A24 6 to 24 Volt Use

SL-126LQ Lens Only



- Easy 2-wire installation, regardless of voltage
- If the strobe light is being powered by a backup battery, as the battery is drained, the strobe light will continue to function
- Perfect for "informative" household burglar alarm use
- Incorrect polarity cannot damage circuit or draw current
- Low current consumption with long operating lifespan of over 300 continuous hours (2,000,000 flashes)
- · Lens is made of high-impact resistant acrylic; case is made of high-impact resistant acrylic
- Choice of amber, blue, clear, green, or red lens

Available in 5 Different Colors:









Green



Amber

Clear

Blue

Red

(SL-126Q)

The SECO-LARM strobe light comes with a protective inner cover. This protects the high-voltage zenon tube when the colored lens has been removed





Specifications:

Model #	SL-126Q	SL-126-A24	
Operating voltage	6~12 VDC	6~24 VDC	
Current draw	200mA±20%@12VDC	150mA±20%@24VDC	
Flash rate	Over 90/min@12VDC	Over 100/min@24VDC	
Candle power	100,000		
Input connections	Red/Positive, Black/Ground		
Leads	#18 Gauge UL Listed	N/A	
Electrical protection	Reverse polarity protected		
Operating life	2,000,000 Flashes (300 hours continuous)		
Operating temperature	-22°~140° F (-30°~60° C)		
Base material	High-impact black ABS		
Lens material	High-impact resistant acrylic		
Dimensions	2 ²⁶ / ₃₂ "x3 ¹⁵ / ₁₆ " (74x100 mm)		

Ordering Information:

	Model #		
Color	6~12 VDC	6~24VDC	Lens Only
Amber	SL-126Q/A	SL-126-A24Q/A	SL-126LQ/A
Clear	SL-126Q/C	SL-126-A24Q/C	SL-126LQ/C
Blue	SL-126Q/B	SL-126-A24Q/B	SL-126LQ/B
Green	SL-126Q/G	SL-126-A24Q/G	SL-126LQ/G
Red	SL-126Q/R	SL-126-A24Q/R	SL-126LQ/R

LED Strobe Lights	SL-1301-BAQ	
Up to 50,000 hours (5.7 years) of continuous use Available in amber, clear, blue green, and red		

SECO-LARM® U.S.A., Inc.

16842 Millikan Ave, Irvine, CA 92606 Tel: 949-261-2999 / 800-662-0800 • Fax: 949-261-7326

sales@seco-larm.com • www.seco-larm.com

The SECO-LARM policy is one of continual development. For that reason, SECO-LARM reserves the right to change prices and specifications without notice. SECO-LARM is not responsible for misprints.





Copyright 2014 © SECO-LARM U.S.A, Inc. All rights reserved.