

Voltage Regulator Module

Single Phase AC Output

multicompPRO

**RoHS
Compliant**



Description

This is single phase voltage regulator module, with phase-shift control output, is widely used in the industrial areas. Control input is 0-10VDC or 4-20mA, output current at 25A, 60A and 80A.

Application

High and low temperature chamber, plastic machinery, incubator, dimmer, solar panel welding machine etc.

Features

- Load Current: 25A, 60A and 80A
- SCR Output
- Control Input: 0-10V DC or 4-20mA
- Phase-shift control output
- LED Indication

Technical Specification

Input Circuit			
Control Signal Parameters	Voltage Range of APS		10-32V DC
	Voltage Control Range		0-10V DC
	Voltage Control	Turn-on Voltage	0.2V DC max
		Turn-off Voltage	0.1V DC min
		Input Resistance	60kΩ Typ.
	Current Control	Control Current	4-20mA
		Turn-on Current	4.6mA max
		Turn-off Current	3.8mA min
		Input Resistance	200Ω Typ.
Output Circuit			
Output Voltage Range	240	176-280V AC	
	480	300-530V AC	
Maximum Surge Current (@10ms)	25A	250A	
	60A	600A	
	80A	800A	
Transient Over voltage	240	600Vpk	
	480	1200Vpk	
Output Power			0-99%
Operating Frequency Range			47-63Hz
Maximum Off-State Leakage Current [@ Rated Voltage]			5mA
Minimum Off-State dv/dt [@ Maximum Rated Voltage]			500V/us

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
Element14.com/multicomp-pro

multicompPRO




multicompPRO

Voltage Regulator Module

Single Phase AC Output

multicompPRO

Thermal Curve



Part Number Table

Description	Part Number
Voltage Regulator Module, Panel Mount, 25A, 240V AC, 0-10VDC, IP20, Power O/P	MC002376
Voltage Regulator Module, Panel Mount, 60A, 240V AC, 0-10VDC, IP20, Power O/P	MC002377
Voltage Regulator Module, Panel Mount, 80A, 240V AC, 0-10VDC, IP20, Power O/P	MC002378
Voltage Regulator Module, Panel Mount, 60A, 240V AC, 4-20mA, IP20, Power O/P	MC002379
Voltage Regulator Module, Panel Mount, 60A, 480V AC, 4-20mA, IP20, Power O/P	MC002380

Important Notice : This data sheet and its contents (the "Information") belong to the members of the AVNET group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp Pro is the registered trademark of Premier Farnell Limited 2019.

Newark.com/multicomp-pro
Farnell.com/multicomp-pro
Element14.com/multicomp-pro

multicompPRO