# **MIH Series 5X7 Ceramic SMD Oscillator**



- o Low Profile SMD Package
- o Hermetically Sealed
- o RoHS Compliant
- o Wide Frequency Range

Frequency Range		1.500MHZ to 156.250MHZ			
Temperature Stability*		(See Part Number Guide for Options)			
Operating Temperature Range		(See Part Number Guide for Options)			
Storage Temperature Range		-55°C to +125°C			
Aging (+25°C ±3°C)		±5ppm for first year			
Waveform		HCMOS			
Supply Voltage ±5% (Vdd)	+1.80 VDC	+2.50 VDC	+3.30 VDC	+5.00 VDC	
Supply Current	15mA	40mA	40mA	70mA	
Load	15pF	15pF	10 TTL Gates or 30pF	10 TTL Gates or 50pF	
Logic "O"		10% Vdd max			
Logic "1"		90% Vdd min			
Rise/Fall Time (10% to 90% of Supply Voltage)		4nSec			
Symmetry (50% of waveform)		40%/60% (45%/55% optional)			
Start-up Time		10mSec max			
Jitter (RMS)		Less than 1 pSec			
Tri-State Operation		Vih = 70% of Vdd min to Enable Output Vil = 30% max or grounded to Disable Output (High Impedance)			
Standby Current Consumption		10uA			

\* Inclusive of Temperature., Load and Voltage

# Mechanical & Environmental Detail

Shock	MIL-STD-883, Method 2002 Cond B		
Solderability	MIL-STD-883, Method 2003		
Solvent Resistance	MIL-STD-202, Method 215		
Vibration	MIL-STD-883, Method 2007, Cond A		
Gross Leak Test	MIL-STD-883, Method 1014, Cond C		
Fine Leak Test	MIL-STD-883, Method 1014, Cond A2		
MSL	Level 1 per IPC/JEDEC J-STD 20		

## **Marking Detail**

Line 1 = MXXXXX				
М	=	MMD		
XXXXX	=	Frequency in MHZ		
Line 2 = SYYWWL				
S	=	Internal Code		
YYWW	=	4 Digit Date Code (Year / Week)		
L	=	Denotes RoHS Compliant		
Line 3 = XXXXX				
Internal use only				
May vary with lots				
Black dot to denote Pin 1				




MMD MONITOR/QUARTZEK – An ILSI Company,

5458 Louie Lane, Reno, NV 89511 Phone: (775) 851-8880, <u>www.mmdcomp.com</u>




AIT Series


### Part Number Guide



Please Consult with MMD Sales Department for any other Parameters or Options  $\,$  \* Not available in +1.8 VDC and +2.5 VDC

# **Mechanical Details**





#### Subject to change without notice