

Accessory for strips 3NJ41 In-line fuse switch disconnectors Sz. NH00 Current transformers can be integrated 150/5 A, Cl. 1



| Model | | |
|--|--|-------|
| product brand name | SETRON | |
| product designation | Current transformer | |
| design of the product | accessory for fuse switch disconnecter 3NJ41 | |
| operating voltage | 0.72 kV | |
| insulation voltage rated value | 3 kV | |
| designation of overcurrent limiting factor | FS 5 | |
| current | | |
| • at input rated value | 150 A | |
| value range of the operating frequency | 50/60 Hz | |
| Protection class | | |
| protection class IP | IP20 | |
| Mechanical Design | | |
| height | 60 mm | |
| width | 46 mm | |
| depth | 19 mm | |
| Net Weight | 229.5 g | |
| Environmental conditions | | |
| ambient temperature during operation | | |
| • minimum | -10 °C | |
| • maximum | 55 °C | |
| Approvals Certificates | | |
| Environment | General Product Approval | other |

[Environmental Confirmations](#)



[Confirmation](#)



[Confirmation](#)

other



Further information

Information on the packaging

<https://support.industry.siemens.com/cs/ww/en/view/109813875>

Information for data generation and storage

<https://support.industry.siemens.com/cs/ww/en/view/109995012>

Information- and Downloadcenter (Catalogs, Brochures,...)

<https://www.siemens.com/lowvoltage/catalogs>

Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3NJ4915-1FB20>

Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3NJ4915-1FB20>

Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, ...)

https://www.automation.siemens.com/bilddb/cax_en.aspx?mlfb=3NJ4915-1FB20

CAX-Online-Generator

<https://www.siemens.com/cax>

Tender specifications

<https://www.siemens.com/specifications>

Characteristic curves

[https://curves.simaris.siemens.com/curves/<mmp_prod_noCOMP="HAUPT"></mmp_prod_no>](https://curves.simaris.siemens.com/curves/<mmp_prod_noCOMP=)

last modified:

6/13/2025 

