


Standard terminal blocks

Compression clamp

 **DIN 1 - 3**

MA 2,5/5...

Spacing 5 mm + 0,08 (.200")



Standard 5 mm block.

0115 486.03

Color	Type	Part numbers
<i>Standard blocks</i>		
Grey	MA 2,5/5	0115 486.03
Blue	MA 2,5/5.N	0125 486.05
Yellow	MA 2,5/5	0105 486.12
White	MA 2,5/5	0105 052.21
Orange	MA 2,5/5	0105 075.20
Beige V0	MA 2,5/5.V0	0195 486.04
Blue V0	MA 2,5/5.N.V0	0199 010.21

Test connector : See Accessories section

End stop	th. 9 mm	BADL V0	0199 408.02
End stop	th. 9,1 mm	BAM	0103 002.26
Rail	35 x 7,5 x 1	PR30 prepunched	0173 220.05
Rail	35 x 15 x 2,3	PR4	0168 500.12
Rail	35 x 15 x 1,5	PR5 prepunched	0101 598.26
Rail	32 x 15 x 1,5	PR1Z2	0163 050.04

Other end stops and rails : See Accessories section

Characteristics

Wire size

	IEC	UL	CSA
	NFC DIN		
Compression Solid wire	0,2-4 mm ²	24-12 AWG	24-12 AWG
clamp Stranded wire	0,22-2,5 mm ²	24-12 AWG	24-12 AWG

Voltage

Rated	800 V	600 V	600 V
Pulse	8 kV		
Pollution degree	3		

Current

Rated	24 A	30 A	25 A
-------	------	------	------

Wire size

Rated / Gauge	2,5 mm ² / A3	12 AWG	12 AWG
Wire stripping length	Recomm. Screwdriver	Recomm. torque	Protection
10 mm	3,5 mm	0,4-0,6 Nm	IP 20
.39"	.137"	3,5-5,3 lb.in	NEMA 1

Notes

The use of some accessories may decrease the block's voltage rating. For more information, consult us.



Accessories

1	End section	grey	
2		blue	
3		orange	
4		yellow	
5		green	
6		white	
7		beige	
8		blue	
9		yellow	
10	End section	grey	
11	End section	grey	
12	Circuit separator	grey	
13	Separator end section	grey	
14		blue	
15		beige	
16	Separator end section	grey	
17	Separator end section	grey	
18	Separator end section	grey	
19	Separator end section	grey	
20	Separator end section	grey	
21	Separator end section	grey	
22	Separator end section	grey	
23	Separator end section	grey	
24	Separator end section	grey	
25	Separator end section	grey	
26	Separator end section	grey	
27	Separator end section	grey	
28	Separator end section	grey	
29	Separator end section	grey	
30	Separator end section	grey	
31	Separator end section	grey	
32	Separator end section	grey	
33	Separator end section	grey	
34	Separator end section	grey	
35	Separator end section	grey	
36	Separator end section	grey	
37	Separator end section	grey	
38	Separator end section	grey	
39	Separator end section	grey	
40	Separator end section	grey	
41	Separator end section	grey	
42	Separator end section	grey	
43	Separator end section	grey	
44	Separator end section	grey	
45	Separator end section	grey	
46	Separator end section	grey	
47	Separator end section	grey	
48	Separator end section	grey	
49	Separator end section	grey	
50	Separator end section	grey	
51	Separator end section	grey	
52	Separator end section	grey	
53	Separator end section	grey	
54	Separator end section	grey	
55	Separator end section	grey	
56	Separator end section	grey	
57	Separator end section	grey	
58	Separator end section	grey	
59	Separator end section	grey	
60	Separator end section	grey	
61	Separator end section	grey	
62	Separator end section	grey	
63	Separator end section	grey	
64	Separator end section	grey	
65	Separator end section	grey	
66	Separator end section	grey	
67	Separator end section	grey	
68	Separator end section	grey	
69	Separator end section	grey	
70	Separator end section	grey	
71	Separator end section	grey	
72	Separator end section	grey	
73	Separator end section	grey	
74	Separator end section	grey	
75	Separator end section	grey	
76	Separator end section	grey	
77	Separator end section	grey	
78	Separator end section	grey	
79	Separator end section	grey	
80	Separator end section	grey	
81	Separator end section	grey	
82	Separator end section	grey	
83	Separator end section	grey	
84	Separator end section	grey	
85	Separator end section	grey	
86	Separator end section	grey	
87	Separator end section	grey	
88	Separator end section	grey	
89	Separator end section	grey	
90	Separator end section	grey	
91	Separator end section	grey	
92	Separator end section	grey	
93	Separator end section	grey	
94	Separator end section	grey	
95	Separator end section	grey	
96	Separator end section	grey	
97	Separator end section	grey	
98	Separator end section	grey	
99	Separator end section	grey	
100	Separator end section	grey	

Type	Part numbers
FEM6 th. 2,8 mm	0118 368.16
FEM6 th. 2,8 mm	0128 368.10
FEM6 th. 2,8 mm	0103 126.16
FEM6 th. 2,8 mm	0103 062.21
FEM6 th. 2,8 mm	0103 125.15
FEM6 th. 2,8 mm	0103 312.20
FEM6 V0 V0 th. 2,8 mm	0198 368.17
FEM6 V0 V0 th. 2,8 mm	0199 302.07
FEM6 V0 V0 th. 2,8 mm	0199 305.02
FEM61 (2) th. 3,0 mm	0114 776.23
FEM6C (2) th. 3,0 mm	0114 777.24
SCMA5	0116 728.25
SCF6 th. 3,0 mm	0118 707.03
SCF6 th. 3,0 mm	0128 707.05
SCF6 V0 V0 th. 3,0 mm	0198 707.04
SCF61 th. 3,0 mm	0114 202.25
SCFM6 (2) th. 3,0 mm	0114 825.05
SCFEX1 (2) th. 2,4 mm	0103 619.04
SCFEX3 (2) th. 2,4 mm	0103 620.01
SCFCV1-2 (2) th. 3,0 mm	0116 795.11
SCFCV1-2 V0(2)V0 th. 3,0 mm	0196 795.12
CPM (for FEM6C, SCF6(V0) and SCFM6)	0187 312.14
CPV1-2 (for SCFCV1-2...)	0176 816.12
AL2 (1) DIA. 2 mm	0163 046.24
DCB blue	0105 028.21
FC2 DIA. 2 mm	0007 865.26
BJM5 (1) 2 poles	0176 273.01
BJM5 (1) 3 poles	0176 274.02
BJM5 (1) 4 poles	0176 275.03
BJM5 (1) 5 poles	0176 276.04
BJM5 (1) 10 poles	0176 277.05
BJMI5 (1) 2 poles	0176 278.16
BJMI5 (1) 3 poles	0176 279.17
BJMI5 (1) 4 poles	0176 280.05
BJMI5 (1) 5 poles	0176 281.22
BJMI5 (1) 10 poles	0176 282.23
BJS5 (1) 20 poles	0177 652.06
EV5	0168 629.16
EL6	0173 627.21
BJE5.2 2 poles	0199 227.23
BJE5.3 3 poles	0199 228.04
BJE5.4 4 poles	0199 298.03
BJE5.5 5 poles	0199 299.04
BJE5.6 6 poles	0299 861.03
BJE5.7 7 poles	0299 862.04
BJE5.8 8 poles	0299 863.05
BJE5.9 9 poles	0299 864.06
BJE5.10 10 poles	0199 443.24
BJB	0199 466.23
BJA5 10 poles	0205 021.26
PC5 2 poles	0113 542.10
PC5 10 poles	0113 544.12
EIP	0113 550.24
CBM5 th. 0,5 mm	0178 745.14
CBM8 th. 0,8 mm	0178 746.15
EPU5	0107 033.10

R See section on markers

marking method

(10) Sides of blocks and RC 510 only, top of blocks

Note : (1) A circuit separator SC may be required with the use of these accessories.
(2) End section and circuit separator snapped on rails.